

Overview

HP 5400R zL2 Switch Series

Models

HP 5406R zL2 Switch	J9821A
HP 5412R zL2 Switch	J9822A
HP 5406R-44G-PoE+/2SFP+ (No PSU) v2 zL2 Switch	J9823A
HP 5412R-92G-PoE+/2SFP+ (No PSU) v2 zL2 Switch	J9825A
HP 5406R-44G-PoE+/4SFP (No PSU) v2 zL2 Switch	J9824A
HP 5412R-92G-PoE+/4SFP (No PSU) v2 zL2 Switch	J9826A
HP 5406R-8XGT/8SFP+ (No PSU) v2 zL2 Switch	J9868A

Key Features

- Advanced access layer, distribution, and core
- Integrated L2 to L4 intelligent edge feature set
- Enterprise-class resiliency with hitless failover, power supply and management module redundancy
- HP AllianceOne integrated
- Scalable 10/100/1000 and 10GbE connectivity with full PoE+ provisioning

Product overview

The HP 5400R zL2 Switch Series consists of advanced intelligent switches with resiliency and redundant management in the HP modular chassis product line, which includes 6-slot and 12-slot chassis and associated modules and bundles. The foundation for the switch series is a purpose-built, programmable ProVision ASIC that allows the most demanding networking features, such as Quality of Service (QoS) and security, to be implemented in a scalable yet granular fashion. With 10/100, Gigabit Ethernet, and 10 Gigabit Ethernet interfaces; choice of PoE+ and non-PoE; integrated Layer 3 features; and HP AllianceOne solutions, the 5400R zL2 switch series offers excellent investment protection, flexibility, and scalability, as well as ease of deployment, operation, and maintenance.

Features and Benefits

Software-defined networking

- **OpenFlow**
supports OpenFlow 1.0 and 1.3 specifications to enable SDN by allowing separation of the data (packet forwarding) and control (routing decision) paths

Quality of Service (QoS)

- **Advanced classifier-based QoS**
classifies traffic using multiple match criteria based on Layer 2, 3, and 4 information; applies QoS policies such as setting priority level and rate limit to selected traffic on a per-port or per-VLAN basis
- **Layer 4 prioritization**
enables prioritization based on TCP/UDP port numbers
- **Traffic prioritization**
allows real-time traffic classification into eight priority levels mapped to eight queues
- **Bandwidth shaping**
 - **Port-based rate limiting**
provides per-port ingress-/egress-enforced increased bandwidth
 - **Classifier-based rate limiting**
uses an access control list (ACL) to enforce increased bandwidth for ingress traffic on each port
 - **Reduced bandwidth**
provides per-port, per-queue egress-based reduced bandwidth

Overview

- **Class of Service (CoS)**
sets the IEEE 802.1p priority tag based on IP address, IP Type of Service (ToS), Layer 3 protocol, TCP/UDP port number, source port, and DiffServ

Management

- **Remote intelligent mirroring**
mirrors selected ingress/egress traffic based on ACL, port, MAC address, or VLAN to a local or remote HP 8200 zL, 6600, 6200 yL, 5400 zL, 5400R, 3500, or 3800 Switch located anywhere on the network
- **RMON, XRMON, and sFlow v5**
provide advanced monitoring and reporting capabilities for statistics, history, alarms, and events
- **IEEE 802.1AB Link Layer Discovery Protocol (LLDP)**
advertises and receives management information from adjacent devices on a network, facilitating easy mapping by network management applications
- **Uni-Directional Link Detection (UDLD)**
monitors a cable between two switches and shuts down the ports on both ends if the cable is broken, turning the bidirectional link into a unidirectional one; this prevents network problems such as loops
- **Management simplicity**
provides common software features and CLI implementation across all HP ProVision-based switches (including the zL and yL switches)
- **Command authorization**
leverages RADIUS to link a custom list of CLI commands to an individual network administrator's login; an audit trail documents activity
- **Friendly port names**
allow assignment of descriptive names to ports
- **Dual flash images**
provides independent primary and secondary operating system files for backup while upgrading
- **Multiple configuration files**
stores easily to the flash image
- **Comware CLI**
 - **Comware-compatible CLI**
bridges the experience of HP Comware CLI users who are using the HP ProVision software CLI
 - **Display and fundamental Comware CLI commands**
are embedded in the switch CLI as native commands; display output formatted as on Comware-based switches; fundamental commands provide a Comware-familiar initial switch setup
 - **Configuration Comware CLI commands**
when Comware commands are entered, CLI help is elicited to formulate the correct ProVision software CLI command

Connectivity

- **IEEE 802.3az Energy Efficient Ethernet**
lowers power consumption in periods of low link usage (supported on v2 zL 10/100/1000 and 10/100 modules)
- **IEEE 802.3af Power over Ethernet (PoE)**
provides up to 15.4 W per port to IEEE 802.3af-compliant PoE-powered devices such as IP phones, wireless access points, and security cameras
- **IEEE 802.3at Power over Ethernet Plus**
provides up to 30 W per port, for up to 288 ports simultaneously, for PoE- and PoE+-powered devices, such as video IP phones, IEEE 802.11n wireless access points, and advanced pan/zoom/tilt security cameras
- **Prestandard PoE support**
detects and provides power to prestandard PoE devices; see the list of supported devices in the product FAQ at: www.hp.com/networking
- **High-density port connectivity**
provides up to 12 interface module slots and up to 288 wire-speed 10/100/1000 PoE-enabled ports or 96 10-GbE ports

Overview

- per system
- **Jumbo frames**
on Gigabit Ethernet and 10-Gigabit Ethernet ports, jumbo frames allow high-performance remote backup and disaster-recovery services
- **Auto-MDIX**
provides automatic adjustments for straight-through or crossover cables on all 10/100 and 10/100/1000 ports
- **IPv6**
 - **IPv6 host**
enables switches to be managed in an IPv6 network
 - **Dual stack (IPv4 and IPv6)**
transitions from IPv4 to IPv6, supporting connectivity for both protocols
 - **MLD snooping**
forwards IPv6 multicast traffic to the appropriate interface
 - **IPv6 ACL/QoS**
supports ACL and QoS for IPv6 network traffic
 - **IPv6 routing**
supports static and OSPFv3 routing protocols
 - **6in4 tunneling**
supports encapsulation of IPv6 traffic in IPv4 packets

Performance

- **High-speed, high-capacity architecture**
2 Tbps crossbar switching fabric provides intra-module and inter-module switching with 785.7 million pps throughput on the purpose-built ProVision ASICs
- **Selectable queue configurations**
allows for increased performance by selecting the number of queues and associated memory buffering that best meet the requirements of the network applications

Resiliency and high availability

- **Virtual Router Redundancy Protocol (VRRP)**
allows groups of two routers to dynamically back each other up to create highly available routed environments for IPv4 and IPv6 networks
- **Nonstop switching**
improves network availability to better support critical applications such as unified communication and mobility; interface and fabric modules continue switching traffic during failover from active to standby management module
- **Nonstop routing**
enhances Layer 3 high availability; OSPFv2/v3 and VRRP will continue to operate and route network traffic during failover from an active to a standby management module
- **Redundant management and power**
provide enhanced system availability and continuity of operations
- **IEEE 802.1s Multiple Spanning Tree Protocol**
provides high link availability in multiple VLAN environments by allowing multiple spanning trees; encompasses IEEE 802.1D Spanning Tree Protocol and IEEE 802.1w Rapid Spanning Tree Protocol
- **IEEE 802.3ad Link Aggregation Control Protocol (LACP) and HP port trunking**
support up to 144 trunks, each with up to eight links (ports) per trunk
- **Distributed trunking**
enables loop-free and redundant network topology without using Spanning Tree Protocol; allows a server or switch to connect to two switches using one logical trunk for redundancy and load sharing
- **Optional redundant power supply**
provides uninterrupted power and allows hot-swapping of the redundant power supplies when installed
- **Hot-swappable modules**
allows dissimilar modules, and power supplies in a redundant power supply configuration to be added or swapped

Overview

- without interrupting the network
- **Sparing simplicity**
HP z1-common accessories (interface modules and power supplies)
- **Uplink Failure Detection**
provides active-standby network path redundancy for servers that are configured for active-standby NIC teaming
- **NEW SmartLink**
provides easy-to-configure link redundancy of active and standby links

Layer 2 switching

- **VLAN support and tagging**
supports the IEEE 802.1Q standard and 2,048 VLANs simultaneously
- **IEEE 802.1v protocol VLANs**
isolate select non-IPv4 protocols automatically into their own VLANs
- **GARP VLAN Registration Protocol**
allows automatic learning and dynamic assignment of VLANs
- **IEEE 802.1ad Q-in-Q**
increases the scalability of an Ethernet network by providing a hierarchical structure; connects multiple LANs on a high-speed campus or metro network
- **MAC-based VLAN**
provides granular control and security; uses RADIUS to map a MAC address/user to specific VLANs (requires v2 modules)
- **Rapid Per-VLAN Spanning Tree (RPVST+)**
allows each VLAN to build a separate spanning tree to improve link bandwidth usage; is compatible with PVST+
- **HP switch meshing**
dynamically load balances across multiple active redundant links to increase available aggregate bandwidth; allows concurrent Layer 3 routing with v2 modules

Layer 3 services

- **User Datagram Protocol (UDP) helper function**
allows UDP broadcasts to be directed across router interfaces to specific IP unicast or subnet broadcast addresses and prevents server spoofing for UDP services such as DHCP
- **Loopback interface address**
defines an address in Routing Information Protocol (RIP) and Open Standard Path First (OSPF), improving diagnostic capability
- **Route maps**
provide more control during route redistribution; allow filtering and altering of route metrics

Layer 3 routing

- **Static IP routing**
provides manually configured routing for both IPv4 and IPv6 networks
- **Routing Information Protocol (RIP)**
provides RIPv1 and RIPv2 routing
- **OSPF**
provides OSPFv2 for IPv4 routing and OSPFv3 for IPv6 routing
- **Policy-based routing**
uses a classifier to select traffic that can be forwarded based on policy set by the network administrator (requires v2 modules)
- **Border Gateway Protocol (BGP)**
provides IPv4 Border Gateway Protocol routing, which is scalable, robust, and flexible

Overview

Security

- **Access control lists (ACLs)**
provide filtering based on the IP field, source/destination IP address/subnet, and source/destination TCP/UDP port number on per-VLAN or per-port basis
- **Multiple user authentication methods**
 - **IEEE 802.1X users per port**
provides authentication of multiple IEEE 802.1X users per port
 - **Web-based authentication**
authenticates from a Web browser for clients that do not support IEEE 802.1X supplicant
 - **MAC-based authentication**
client is authenticated with the RADIUS server based on the client's MAC address
 - **Concurrent IEEE 802.1X, Web, and MAC authentication schemes per port**
switch port accepts up to 32 sessions of IEEE 802.1X, Web, and MAC authentications
- **Virus throttling**
detects traffic patterns typical of worm-type viruses and either throttles or entirely prevents the virus from spreading across the routed VLANs or bridged interfaces without requiring external appliances
- **DHCP protection**
blocks DHCP packets from unauthorized DHCP servers, preventing denial-of-service attacks
- **Secure management access**
delivers secure encryption of all access methods (CLI, GUI, or MIB) through SSHv2, SSL, and/or SNMPv3
- **Switch CPU protection**
provides automatic protection against malicious network traffic trying to shut down the switch
- **ICMP throttling**
defeats ICMP denial-of-service attacks by enabling any switch port to automatically throttle ICMP traffic
- **Identity-driven ACL**
enables implementation of a highly granular and flexible access security policy and VLAN assignment specific to each authenticated network user
- **STP BPDU port protection**
blocks Bridge Protocol Data Units (BPDUs) on ports that do not require BPDUs, preventing forged BPDU attacks
- **Dynamic IP lockdown**
works with DHCP protection to block traffic from unauthorized hosts, preventing IP source address spoofing
- **Dynamic ARP protection**
blocks ARP broadcasts from unauthorized hosts, preventing eavesdropping or theft of network data
- **STP Root Guard**
protects the root bridge from malicious attacks or configuration mistakes
- **Detection of malicious attacks**
monitors 10 types of network traffic and sends a warning when an anomaly that potentially can be caused by malicious attacks is detected
- **Port security**
allows access only to specified MAC addresses, which can be learned or specified by the administrator
- **MAC address lockout**
prevents particular configured MAC addresses from connecting to the network
- **Source-port filtering**
allows only specified ports to communicate with each other
- **RADIUS/TACACS+**
eases switch management security administration by using a password authentication server
- **Secure Shell**
encrypts all transmitted data for secure remote CLI access over IP networks
- **Secure Sockets Layer (SSL)**
encrypts all HTTP traffic, allowing secure access to the browser-based management GUI in the switch
- **Secure FTP**
allows secure file transfer to and from the switch; protects against unwanted file downloads or unauthorized copying of a switch configuration file

Overview

- **Management Interface Wizard**
helps secure management interfaces such as SNMP, telnet, SSH, SSL, Web, and USB at the desired level
- **Switch management logon security**
helps secure switch CLI logon by optionally requiring either RADIUS or TACACS+ authentication
- **Security banner**
displays a customized security policy when users log in to the switch

Convergence

- **IP multicast routing**
includes PIM Sparse and Dense modes to route IP multicast traffic
- **IP multicast snooping** (data-driven IGMP)
automatically prevents flooding of IP multicast traffic
- **LLDP-MED (Media Endpoint Discovery)**
is a standard extension of LLDP that stores values for parameters such as QoS and VLAN to automatically configure network devices such as IP phones
- **PoE allocations**
support multiple methods (automatic, IEEE 802.3af class, LLDP-MED, or user specified) to allocate PoE power for more efficient energy savings
- **Auto VLAN configuration for voice**
 - RADIUS VLAN: uses a standard RADIUS attribute and LLDP-MED to automatically configure a VLAN for IP phones
 - CDPv2: uses CDPv2 to configure legacy IP phones
- **Local MAC Authentication**
assigns attributes such as VLAN and QoS using locally configured profile that can be a list of MAC prefixes

Warranty and support

- **Lifetime Warranty 2.0**
advance hardware replacement for as long as you own the product with next-business-day delivery (available in most countries)†
- **Electronic and telephone support (for Lifetime Warranty 2.0)**
limited 24x7 telephone support is available from HP for the first 3 years; limited electronic and business hours telephone support is available from HP for the entire warranty period; to reach our support centers, refer to www.hp.com/networking/contact-support; for details on the duration of support provided with your product purchase, refer to www.hp.com/networking/warrantysummary
- **Software releases**
to find software for your product, refer to www.hp.com/networking/support; for details on the software releases available with your product purchase, refer to www.hp.com/networking/warrantysummary

†HP warranty includes repair or replacement of hardware for as long as you own the product, with next business day advance replacement (available in most countries). The disk drive included with HP AllianceOne Advanced Services and Services z1 Modules, HP Threat Management Services z1 Module, HP AllianceOne Extended z1 Module with Riverbed Steelhead, HP MSM765z1 Mobility Controller and HP Survivable Branch Communication z1 Module powered by Microsoft Lync has a five-year hardware warranty. For details, refer to the Software license and hardware warranty statements at: www.hp.com/networking/warranty.

Configuration

Build To Order:

BTO is a standalone unit with no integration. BTO products ship standalone are not part of a CTO or Rack-Shippable solution.

HP 5406 zL Switch with Premium Software	J9642A
<ul style="list-style-type: none"> 1 Power Supply required 4U - Height 	
HP 5406R zL2 Switch	J9821A
<ul style="list-style-type: none"> 1 Power Supply required 1 Fan Tray Included 1 Management module included 1 RJ-45 out-of-band management port 4U - Height 	
HP 5406-44G-PoE+-2XG v2 zL Swch w Pm SW	J9533A
<ul style="list-style-type: none"> 44 autosensing 10/100/1000 port 1 - J9306A HP 1500 W PoE+ zL Power Supply included 1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included (min=0 \ max=2 SFP+ Transceivers) 1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included 4U - Height 	See Configuration Note:1, 5, 9
PDU Cable NA/MEX/TW/JP	J9533A#B2B
<ul style="list-style-type: none"> C15 PDU Jumper Cord (NA/MEX/TW/JP) 	
PDU Cable ROW	J9533A#B2C
<ul style="list-style-type: none"> C15 PDU Jumper Cord (ROW) 	
High Volt Switch to Wall Power Cord	J9533A#B2E
<ul style="list-style-type: none"> NEMA L6-20P Cord (NA/MEX/JP/TW) 	
HP 5406-44G-PoE+-4G v2 zL Swch w Prm SW	J9539A
<ul style="list-style-type: none"> 44 autosensing 10/100/1000 port 1 - J9306A HP 1500 W PoE+ zL Power Supply included 1 - J9535A HP 20-port GT PoE+/4-port SFP v2 zL Mod included (min=0 \ max=4 SFP Transceivers) 1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included 4U - Height 	See Configuration Note:2, 5, 9
PDU Cable NA/MEX/TW/JP	J9539A#B2B
<ul style="list-style-type: none"> C15 PDU Jumper Cord (NA/MEX/TW/JP) 	
PDU Cable ROW	J9539A#B2C
<ul style="list-style-type: none"> C15 PDU Jumper Cord (ROW) 	
High Volt Switch to Wall Power Cord	J9539A#B2E
<ul style="list-style-type: none"> NEMA L6-20P Cord (NA/MEX/JP/TW) 	
HP 5406 8p10GT 8p10GE Swch and Psw	J9866A

Configuration

<ul style="list-style-type: none">8 RJ-45 10GbE ports1 - J9306A HP 1500 W PoE+ zL Power Supply included1 - J9546A HP 8-port 10GBASE-T v2 zL Module included1 - J9538A HP 8-port 10GbE SFP+ v2 zL Module included (min=0 \ max=8 SFP+ Transceivers)4U - Height	See Configuration Note:1, 5, 9
<p>PDU Cable NA/MEX/TW/JP</p> <ul style="list-style-type: none">C15 PDU Jumper Cord (NA/MEX/TW/JP)	J9866A#B2B
<p>PDU Cable ROW</p> <ul style="list-style-type: none">C15 PDU Jumper Cord (ROW)	J9866A#B2C
<p>High Volt Switch to Wall Power Cord</p> <ul style="list-style-type: none">NEMA L6-20P Cord (NA/MEX/JP/TW)	J9866A#B2E
<p>HP 5406R-8XGT/8SFP+ v2 zL2 Swch</p> <ul style="list-style-type: none">1 Power Supply required8 RJ-45 10GbE ports1 - J9546A HP 8-port 10GBASE-T v2 zL Module included1 - J9538A HP 8-port 10GbE SFP+ v2 zL Module included (min=0 \ max=8 SFP+ Transceivers)1 Fan Tray Included1 Management module included1 RJ-45 out-of-band management port4U - Height	J9868A See Configuration Note:1
<p>HP 5406R-Gig-T-PoE+/SFP+ v2 zL2 Swch</p> <ul style="list-style-type: none">1 Power Supply required1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included(min=0 \ max=2 SFP+ Transceivers)1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included1 Fan Tray Included1 Management module included1 RJ-45 out-of-band management port4U - Height	J9823A See Configuration Note:1
<p>HP 5406R-Gig-T-PoE+/SFP v2 zL2 Swch</p> <ul style="list-style-type: none">1 Power Supply required1 - J9535A HP 20-port Gig-T PoE+ / 4-port SFP v2 zL Module included (min=0 \ max=4 SFP Transceivers)1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included1 Fan Tray Included1 Management module included1 RJ-45 out-of-band management port4U - Height	J9824A See Configuration Note:2
<p>HP 5412 zL Switch with Premium Software</p> <ul style="list-style-type: none">2 Power Supplies required7U - Height	J9643A
<p>HP 5412R zL2 Switch</p> <ul style="list-style-type: none">2 Power Supplies required	J9822A

Configuration

- 1 Fan Tray Included
- 1 Management module included
- 1 RJ-45 out-of-band management port
- 7U - Height

HP 5412-92G-PoE+-2XG v2 zL Swch w Pm SW

- 92 autosensing 10/100/1000 port
- 2 - J9306A HP 1500 W PoE+ zL Power Supply included
- 1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included(min=0 \ max=2 SFP+ Transceivers)
- 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
- 7U - Height

J9532A
See Configuration
Note:1, 5, 9

PDU Cable NA/MEX/TW/JP

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

J9532A#B2B

PDU Cable ROW

- C15 PDU Jumper Cord (ROW)

J9532A#B2C

High Volt Switch to Wall Power Cord

- NEMA L6-20P Cord (NA/MEX/JP/TW)

J9532A#B2E

HP 5412-92G-PoE+-4G v2 zL Swch w Prm SW

- 92 autosensing 10/100/1000 port
- 2 - J9306A HP 1500 W PoE+ zL Power Supply included
- 1 - J9535A HP 20-port Gig-T PoE+ / 4-port SFP v2 zL Module included (min=0 \ max=4 SFP Transceivers)
- 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
- 7U - Height

J9540A
See Configuration
Note:2, 5, 9

PDU Cable NA/MEX/TW/JP

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

J9540A#B2B

PDU Cable ROW

- C15 PDU Jumper Cord (ROW)

J9540A#B2C

High Volt Switch to Wall Power Cord

- NEMA L6-20P Cord (NA/MEX/JP/TW)

J9540A#B2E

HP 5412R-Gig-T-PoE+/SFP+ v2 zL2 Swch

- 2 Power Supplies required
- 1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included(min=0 \ max=2 SFP+ Transceivers)
- 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
- 1 Fan Tray Included
- 1 Management module included
- 1 RJ-45 out-of-band management port
- 7U - Height

J9825A
See Configuration
Note:1

HP 5412R-Gig-T-PoE+/SFP v2 zL2 Swch

J9826A

Configuration

2 Power Supplies required See Configuration Note:2
 1 - J9535A HP 20-port Gig-T PoE+ / 4-port SFP v2 zL Module included (min=0 \ max=4 SFP Transceivers)
 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
 1 Fan Tray Included
 1 Management module included
 1 RJ-45 out-of-band management port
 7U – Height

Configuration Rules:

Note 1 The following Transceivers install into this Chassis :

HP X121 1G SFP LC SX Transceiver	J4858C
HP X121 1G SFP LC LX Transceiver	J4859C
HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP RJ45 T Transceiver	J8177C
HP X122 1G SFP LC BX-D Transceiver	J9142B
HP X122 1G SFP LC BX-U Transceiver	J9143B
HP X132 10G SFP+ LC ER Transceiver	J9153A
HP X132 10G SFP+ LC LR Transceiver	J9151A
HP X132 10G SFP+ LC LRM Transceiver	J9152A
HP X132 10G SFP+ LC SR Transceiver	J9150A
HP X242 10G SFP+ to SFP+ 1m Direct Attach Copper Cable	J9281B
HP X242 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	J9283B
HP X242 10G SFP+ to SFP+ 7m Direct Attach Copper Cable	J9285B
HP X244 10G XFP to SFP+ 1m Direct Attach Copper Cable	J9300A
HP 10G X244 XFP to SFP+ 3m Direct Attach Copper Cable	J9301A
HP 10G X244 XFP to SFP+ 5m Direct Attach Copper Cable	J9302A

Note 2 The following Transceivers install into this switch:

HP X121 1G SFP LC SX Transceiver	J4858C
HP X121 1G SFP LC LX Transceiver	J4859C
HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP RJ45 T Transceiver	J8177C
HP X112 100M SFP LC BX-D Transceiver	J9099B
HP X112 100M SFP LC BX-U Transceiver	J9100B
HP X122 1G SFP LC BX-D Transceiver	J9142B
HP X122 1G SFP LC BX-U Transceiver	J9143B
HP X111 100M SFP LC FX Transceiver	J9054C

Note 5 If #B2E is selected Then replace Localized option with #B2E for power supply and with #B2E for switch . (Offered only in North America, Mexico Taiwan, and Japan)

Note 9 Localization required on orders without #B2B, #B2C or #B2E options.

Box Level Integration CTO Models

CTO Solution Sku

HP 54xx CTO Switch Solution	J9809A
<ul style="list-style-type: none"> SSP trigger sku 	

Configuration

CTO Switch Chassis

HP 5406 zL Switch with Premium Software

1 Power Supply required

- 4U - Height

J9642A

See Configuration
Note:4, 10

HP 5406R zL2 Switch

- 1 Power Supply required
- 1 Fan Tray Included
- 1 Management module included
- 1 RJ-45 out-of-band management port
- 4U - Height

J9821A

See Configuration
Note:10

HP 5406-44G-PoE+-2XG v2 zL Swch w Pm SW

- 44 autosensing 10/100/1000 port
- 1 - J9306A HP 1500 W PoE+ zL Power Supply included
- 1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included (min=0 \ max=2 SFP+ Transceivers)
- 1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
- 4U - Height

J9533A

See Configuration
Note:1, 4, 8, 10, 12

PDU Cable NA/MEX/TW/JP

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

J9533A#B2B

PDU Cable ROW

- C15 PDU Jumper Cord (ROW)

J9533A#B2C

High Volt Switch to Wall Power Cord

- NEMA L6-20P Cord (NA/MEX/JP/TW)

J9533A#B2E

HP 5406-44G-PoE+-4G v2 zL Swch w Prm SW

- 44 autosensing 10/100/1000 port
- 1 - J9306A HP 1500 W PoE+ zL Power Supply included
- 1 - J9535A HP 20-port GT PoE+/4-port SFP v2 zL Mod included (min=0 \ max=4 SFP Transceivers)
- 1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
- 4U - Height

J9539A

See Configuration Note:
2, 4, 8, 10, 12

PDU Cable NA/MEX/TW/JP

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

J9539A#B2B

PDU Cable ROW

- C15 PDU Jumper Cord (ROW)

J9539A#B2C

High Volt Switch to Wall Power Cord

- NEMA L6-20P Cord (NA/MEX/JP/TW)

J9539A#B2E

HP 5406 8p10GT 8p10GE Swch and Psw

- 8 RJ-45 10GbE ports

J9866A

See Configuration

Configuration

<ul style="list-style-type: none">1 - J9306A HP 1500 W PoE+ zL Power Supply included1 - J9546A HP 8-port 10GBASE-T v2 zL Module included1 - J9538A HP 8-port 10GbE SFP+ v2 zL Module included (min=0 \ max=8 SFP+ Transceivers)4U - Height	Note:1, 4, 8, 10, 12
<p>PDU Cable NA/MEX/TW/JP</p> <ul style="list-style-type: none">C15 PDU Jumper Cord (NA/MEX/TW/JP)	J9866A#B2B
<p>PDU Cable ROW</p> <ul style="list-style-type: none">C15 PDU Jumper Cord (ROW)	J9866A#B2C
<p>High Volt Switch to Wall Power Cord</p> <ul style="list-style-type: none">NEMA L6-20P Cord (NA/MEX/JP/TW)	J9866A#B2E
<p>HP 5406R-8XGT/8SFP+ v2 zL2 Swch</p> <ul style="list-style-type: none">1 Power Supply required8 RJ-45 10GbE ports1 - J9546A HP 8-port 10GBASE-T v2 zL Module included1 - J9538A HP 8-port 10GbE SFP+ v2 zL Module included (min=0 \ max=8 SFP+ Transceivers)1 Fan Tray Included1 Management module included1 RJ-45 out-of-band management port4U - Height	J9868A See Configuration Note:1, 10
<p>HP 5406R-Gig-T-PoE+/SFP+ v2 zL2 Swch</p> <ul style="list-style-type: none">1 Power Supply required1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included(min=0 \ max=2 SFP+ Transceivers)1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included1 Fan Tray Included1 Management module included1 RJ-45 out-of-band management port4U - Height	J9823A See Configuration Note:1, 10
<p>HP 5406R-Gig-T-PoE+/SFP v2 zL2 Swch</p> <ul style="list-style-type: none">1 Power Supply required1 - J9535A HP 20-port Gig-T PoE+ / 4-port SFP v2 zL Module included (min=0 \ max=4 SFP Transceivers)1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included1 Fan Tray Included1 Management module included1 RJ-45 out-of-band management port4U - Height	J9824A See Configuration Note:2, 10
<p>HP 5412 zL Switch with Premium Software</p> <ul style="list-style-type: none">2 Power Supplies required7U - Height	J9643A See Configuration Note:4, 10
<p>HP 5412R zL2 Switch</p> <ul style="list-style-type: none">2 Power Supplies required1 Fan Tray Included	J9822A See Configuration Note:10

Configuration

- 1 Management module included
- 1 RJ-45 out-of-band management port
- 7U - Height

HP 5412-92G-PoE+-2XG v2 zL Swch w Pm SW

- 92 autosensing 10/100/1000 port
- 2 - J9306A HP 1500 W PoE+ zL Power Supply included
- 1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included(min=0 \ max=2 SFP+ Transceivers)
- 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
- 7U - Height

J9532A

See Configuration
Note:1, 4, 8, 10, 12

PDU Cable NA/MEX/TW/JP

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

J9532A#B2B

PDU Cable ROW

- C15 PDU Jumper Cord (ROW)

J9532A#B2C

High Volt Switch to Wall Power Cord

- NEMA L6-20P Cord (NA/MEX/JP/TW)

J9532A#B2E

HP 5412-92G-PoE+-4G v2 zL Swch w Prm SW

- 92 autosensing 10/100/1000 port
- 2 - J9306A HP 1500 W PoE+ zL Power Supply included
- 1 - J9535A HP 20-port Gig-T PoE+ / 4-port SFP v2 zL Module included (min=0 \ max=4 SFP Transceivers)
- 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
- 7U - Height

J9540A

See Configuration
Note:2, 4, 8, 10, 12

PDU Cable NA/MEX/TW/JP

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

J9540A#B2B

PDU Cable ROW

- C15 PDU Jumper Cord (ROW)

J9540A#B2C

High Volt Switch to Wall Power Cord

- NEMA L6-20P Cord (NA/MEX/JP/TW)

J9540A#B2E

HP 5412R-Gig-T-PoE+/SFP+ v2 zL2 Swch

- 2 Power Supplies required
- 1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included(min=0 \ max=2 SFP+ Transceivers)
- 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
- 1 Fan Tray Included
- 1 Management module included
- 1 RJ-45 out-of-band management port
- 7U - Height

J9825A

See Configuration
Note:1, 10

HP 5412R-Gig-T-PoE+/SFP v2 zL2 Swch

- 2 Power Supplies required

J9826A

See Configuration
Note:2, 10

Configuration

- 1 - J9535A HP 20-port Gig-T PoE+ / 4-port SFP v2 z1 Module included (min=0 \ max=4 SFP Transceivers)
- 3 - J9534A HP 24-port Gig-T PoE+ v2 z1 Module included
- 1 Fan Tray Included
- 1 Management module included
- 1 RJ-45 out-of-band management port
- 7U - Height

Note 1 The following Transceivers install into this Chassis : (Use #0D1 or #B01 if switch is CTO) - if applicable

HP X121 1G SFP LC SX Transceiver	J4858C
HP X121 1G SFP LC LX Transceiver	J4859C
HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP RJ45 T Transceiver	J8177C
HP X122 1G SFP LC BX-D Transceiver	J9142B
HP X122 1G SFP LC BX-U Transceiver	J9143B
HP X132 10G SFP+ LC ER Transceiver	J9153A
HP X132 10G SFP+ LC LR Transceiver	J9151A
HP X132 10G SFP+ LC LRM Transceiver	J9152A
HP X132 10G SFP+ LC SR Transceiver	J9150A
HP X242 10G SFP+ to SFP+ 1m Direct Attach Copper Cable	J9281B
HP X242 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	J9283B
HP X242 10G SFP+ to SFP+ 7m Direct Attach Copper Cable	J9285B
HP X244 10G XFP to SFP+ 1m Direct Attach Copper Cable	J9300A
HP 10G X244 XFP to SFP+ 3m Direct Attach Copper Cable	J9301A
HP 10G X244 XFP to SFP+ 5m Direct Attach Copper Cable	J9302A

Note 2 The following Transceivers install into this Chassis : (Use #0D1 if switch is CTO) - if applicable

HP X121 1G SFP LC SX Transceiver	J4858C
HP X121 1G SFP LC LX Transceiver	J4859C
HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP RJ45 T Transceiver	J8177C
HP X112 100M SFP LC BX-D Transceiver	J9099B
HP X112 100M SFP LC BX-U Transceiver	J9100B
HP X122 1G SFP LC BX-D Transceiver	J9142B
HP X122 1G SFP LC BX-U Transceiver	J9143B
HP X111 100M SFP LC FX Transceiver	J9054C

Note 4 Localization required on orders without #B2B, #B2C or #B2E options.

Note 8 If #B2E is selected Then replace Localized option with #B2E for power supply and with #B2E for switch . (Offered only in North America, Mexico Taiwan, and Japan)

Note 10 If the Switch Chassis is to be Factory Integrated (CTO), Then the #0D1 is required on the Switch Chassis and integrated to the J9809A - HP 5400 CTO Enablement. (Min 1/Max 1 Switch per SSP)

Note 12 If this Switch is selected, Then a Minimum of 1 factory integrated accessory must be ordered and integrated to CTO chassis. See Menu below, option must have a #0D1 to be integrated to the CTO Chassis.

Configuration

Rack Level Integration CTO Models

CTO Switch Chassis

HP 5406 zL Switch with Premium Software

- 1 Power Supply required
- 4U - Height

J9642A
See Configuration
Note:11

HP 5406R zL2 Switch

- 1 Power Supply required
- 1 Fan Tray Included
- 1 Management module included
- 1 RJ-45 out-of-band management port
- 4U - Height

J9821A
See Configuration
Note:11

HP 5406-44G-PoE+-2XG v2 zL Swch w Pm SW

- 44 autosensing 10/100/1000 port
- 1 - J9306A HP 1500 W PoE+ zL Power Supply included
- 1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included (min=0 \ max=2 SFP+ Transceivers)
- 1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
- 4U - Height

J9533A
See Configuration
Note:1, 4, 11

PDU Cable NA/MEX/TW/JP

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

J9533A#B2B

PDU Cable ROW

- C15 PDU Jumper Cord (ROW)

J9533A#B2C

HP 5406-44G-PoE+-4G v2 zL Swch w Prm SW

- 44 autosensing 10/100/1000 port
- 1 - J9306A HP 1500 W PoE+ zL Power Supply included
- 1 - J9535A HP 20-port GT PoE+/4-port SFP v2 zL Mod included (min=0 \ max=4 SFP Transceivers)
- 1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included
- 4U - Height

J9539A
See Configuration
Note:2, 4, 11

PDU Cable NA/MEX/TW/JP

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

J9539A#B2B

PDU Cable ROW

- C15 PDU Jumper Cord (ROW)

J9539A#B2C

HP 5406 8p10GT 8p10GE Swch and Psw

- 8 RJ-45 10GbE ports
- 1 - J9306A HP 1500 W PoE+ zL Power Supply included
- 1 - J9546A HP 8-port 10GBASE-T v2 zL Module included
- 1 - J9538A HP 8-port 10GbE SFP+ v2 zL Module included (min=0 \ max=8 SFP+ Transceivers)
- 4U - Height

J9866A
See Configuration
Note:1, 4, 11

Configuration

PDU Cable NA/MEX/TW/JP	J9866A#B2B
<ul style="list-style-type: none"> • C15 PDU Jumper Cord (NA/MEX/TW/JP) 	
PDU Cable ROW	J9866A#B2C
<ul style="list-style-type: none"> • C15 PDU Jumper Cord (ROW) 	
HP 5406R-8XGT/8SFP+ v2 zL2 Swch	J9868A
<ul style="list-style-type: none"> • 1 Power Supply required • 8 RJ-45 10GbE ports • 1 - J9546A HP 8-port 10GBASE-T v2 zL Module included • 1 - J9538A HP 8-port 10GbE SFP+ v2 zL Module included (min=0 \ max=8 SFP+ Transceivers) • 1 Fan Tray Included • 1 Management module included • 1 RJ-45 out-of-band management port • 4U - Height 	See Configuration Note:1, 11
HP 5406R-Gig-T-PoE+/SFP+ v2 zL2 Swch	J9823A
<ul style="list-style-type: none"> • 1 Power Supply required • 1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included(min=0 \ max=2 SFP+ Transceivers) • 1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included • 1 Fan Tray Included • 1 Management module included • 1 RJ-45 out-of-band management port • 4U - Height 	See Configuration Note:1, 11
HP 5406R-Gig-T-PoE+/SFP v2 zL2 Swch	J9824A
<ul style="list-style-type: none"> • 1 Power Supply required • 1 - J9535A HP 20-port Gig-T PoE+ / 4-port SFP v2 zL Module included (min=0 \ max=4 SFP Transceivers) • 1 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included • 1 Fan Tray Included • 1 Management module included • 1 RJ-45 out-of-band management port • 4U - Height 	See Configuration Note:2, 11
HP 5412 zL Switch with Premium Software	J9643A
<ul style="list-style-type: none"> • 2 Power Supplies required • 7U - Height 	See Configuration Note:11
HP 5412R zL2 Switch	J9822A
<ul style="list-style-type: none"> • 2 Power Supplies required • 1 Fan Tray Included • 1 Management module included • 1 RJ-45 out-of-band management port • 7U - Height 	See Configuration Note:11
HP 5412-92G-PoE+-2XG v2 zL Swch w Pm SW	J9532A
<ul style="list-style-type: none"> • 92 autosensing 10/100/1000 port • 2 - J9306A HP 1500 W PoE+ zL Power Supply included • 1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included(min=0 \ max=2 	See Configuration Note:1, 4, 11

Configuration

<ul style="list-style-type: none"> SFP+ Transceivers) <ul style="list-style-type: none"> 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included 7U - Height 		
PDU Cable NA/MEX/TW/JP		J9532A#B2B
<ul style="list-style-type: none"> C15 PDU Jumper Cord (NA/MEX/TW/JP) 		
PDU Cable ROW		J9532A#B2C
<ul style="list-style-type: none"> C15 PDU Jumper Cord (ROW) 		
HP 5412-92G-PoE+-4G v2 zL Swch w Prm SW		J9540A
<ul style="list-style-type: none"> 92 autosensing 10/100/1000 port 2 - J9306A HP 1500 W PoE+ zL Power Supply included 1 - J9535A HP 20-port Gig-T PoE+ / 4-port SFP v2 zL Module included (min=0 \ max=4 SFP Transceivers) 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included 7U - Height 		See Configuration Note:2, 4, 11
PDU Cable NA/MEX/TW/JP		J9540A#B2B
<ul style="list-style-type: none"> C15 PDU Jumper Cord (NA/MEX/TW/JP) 		
PDU Cable ROW		J9540A#B2C
<ul style="list-style-type: none"> C15 PDU Jumper Cord (ROW) 		
HP 5412R-Gig-T-PoE+/SFP+ v2 zL2 Swch		J9825A
<ul style="list-style-type: none"> 2 Power Supplies required 1 - J9536A HP 20-port Gig-T PoE+ / 2-port 10-GbE SFP+ v2 zL Module included(min=0 \ max=2 SFP+ Transceivers) 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included 1 Fan Tray Include 1 Management module included 1 RJ-45 out-of-band management port 7U - Height 		See Configuration Note:1, 11
HP 5412R-Gig-T-PoE+/SFP v2 zL2 Swch		J9826A
<ul style="list-style-type: none"> 2 Power Supplies required 1 - J9535A HP 20-port Gig-T PoE+ / 4-port SFP v2 zL Module included (min=0 \ max=4 SFP Transceivers) 3 - J9534A HP 24-port Gig-T PoE+ v2 zL Module included 1 Fan Tray Included 1 Management module included 1 RJ-45 out-of-band management port 7U - Height 		See Configuration Note:2, 11

Configuration Rules:

Note 1 The following Transceivers install into this Chassis : (Use #0D1 or #B01 if switch is CTO) - if applicable

HP X121 1G SFP LC SX Transceiver
 HP X121 1G SFP LC LX Transceiver

J4858C
 J4859C

Configuration

HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP RJ45 T Transceiver	J8177C
HP X122 1G SFP LC BX-D Transceiver	J9142B
HP X122 1G SFP LC BX-U Transceiver	J9143B
HP X132 10G SFP+ LC ER Transceiver	J9153A
HP X132 10G SFP+ LC LR Transceiver	J9151A
HP X132 10G SFP+ LC LRM Transceiver	J9152A
HP X132 10G SFP+ LC SR Transceiver	J9150A
HP X242 10G SFP+ to SFP+ 1m Direct Attach Copper Cable	J9281B
HP X242 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	J9283B
HP X242 10G SFP+ to SFP+ 7m Direct Attach Copper Cable	J9285B
HP X244 10G XFP to SFP+ 1m Direct Attach Copper Cable	J9300A
HP 10G X244 XFP to SFP+ 3m Direct Attach Copper Cable	J9301A
HP 10G X244 XFP to SFP+ 5m Direct Attach Copper Cable	J9302A

Note 2 The following Transceivers install into this Chassis : (Use #0D1 if switch is CTO) - if applicable

HP X121 1G SFP LC SX Transceiver	J4858C
HP X121 1G SFP LC LX Transceiver	J4859C
HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP RJ45 T Transceiver	J8177C
HP X112 100M SFP LC BX-D Transceiver	J9099B
HP X112 100M SFP LC BX-U Transceiver	J9100B
HP X122 1G SFP LC BX-D Transceiver	J9142B
HP X122 1G SFP LC BX-U Transceiver	J9143B
HP X111 100M SFP LC FX Transceiver	J9054C

Note 4 Localization required on orders without #B2B, #B2C or #B2E options.

Note 11 If the CTO Switch Chassis needs to be racked, Then the CTO Base Model needs to integrate (with #0D1) to the HP Rack.

Modules

Management Modules

(J9821A, J9868A, J9823A, J9824A, J9822A, J9825A, J9826A) System (std 1 // max 2) User Selection (min 0 / max 1)

HP 5400R zL2 Management Module	J9827A
<ul style="list-style-type: none"> No Transceivers 	

I/O Modules

J9642A only - System (std 0 // max=6) User Selection (min 0 / max=6) per Chassis

J9821A only - System (std 0 // max=6) User Selection (min 0 / max=6) per Chassis

J9643A only - System (std 0 // max=12) User Selection (min 0 / max=12) per Chassis

Configuration

J9822A only - System (std 0 // max=12) User Selection (min 0 / max=12) per Chassis

J9533A, J9539A, J9866A only - System (std 2 // max=6) User Selection (min 0 / max=4) per Chassis

J9868A, J9823A, J9824A only - System (std 2 // max=6) User Selection (min 0 / max=4) per Chassis

J9532A, J9540A only - System (std 4 // max=12) User Selection (min 0 / max=8) per Chassis

J9825A, J9826A only - System (std 4 // max=12) User Selection (min 0 / max=8) per Chassis

HP 20-port GT PoE+/4-port SFP v2 z1 Mod

- min=0 \ max=4 SFP Transceivers

J9535A
See Configuration
Note:1

HP 24-port SFP v2 z1 Module

- min=0 \ max=24 SFP Transceivers

J9537A
See Configuration
Note:1

HP 12p Gig-T PoE+/12p SFP v2 z1 Mod

- min=0 \ max=12 SFP Transceivers

J9637A
See Configuration
Note:1

HP 20-port Gig-T / 4-port SFP v2 z1 Mod

- min=0 \ max=4 SFP Transceivers

J9549A
See Configuration
Note:1

HP 4-port 10GbE SFP+ z1 Module

- min=0 \ max=4 SFP+ Transceivers

J9309A
See Configuration
Note:2, 13

HP 8-port 10 GbE SFP+ v2 z1 Module

- min=0 \ max=8 SFP+ Transceivers

J9538A
See Configuration
Note:5

•

HP 20p GT PoE+ / 2p SFP+ v2 z1 Module

- min=0 \ max=2 SFP+ Transceivers

J9536A
See Configuration
Note:5

HP 20-port Gig-T / 2-port SFP+ v2 z1 Mod

- min=0 \ max=2 SFP+ Transceivers

J9548A
See Configuration
Note:5

HP 4-Port 10 GbE X2 z1 Module

- min=0 \ max=2 X2 Transceivers

J8707A
See Configuration
Note:3, 13

HP 4-Port 10 GbE CX4 z1 Module

- min=0 \ max=2 CX4 Media Converter

J8708A
See Configuration
Note:13

HP 8-port 10GBase-T v2 z1 Module

- No Transceivers

J9546A

Configuration

HP 24-Port 10/100/1000 PoE z1 Module <ul style="list-style-type: none">No Transceivers	J8702A See Configuration Note:13
HP 20p 10/100/1000 PoE+/4p MGBIC z1 Mod <ul style="list-style-type: none">min=0 \ max=4 SFP Transceivers	J9308A See Configuration Note:1, 13
HP 20-Port Gig-T/4-Port Mini-GBIC z1 Module <ul style="list-style-type: none">min=0 \ max=4 SFP Transceivers	J8705A See Configuration Note:12, 13
HP 24-Port Mini-GBIC z1 Module <ul style="list-style-type: none">min=0 \ max=24 SFP Transceivers	J8706A See Configuration Note:12, 13
HP 24-Port 10/100/1000 PoE+ z1 Module <ul style="list-style-type: none">No Transceivers	J9307A See Configuration Note:13
HP 24-port Gig-T PoE+ v2 z1 Module <ul style="list-style-type: none">No Transceivers	J9534A
HP 24-Port 10/100 PoE+ z1 Module <ul style="list-style-type: none">No Transceivers	J9478A See Configuration Note:13
HP 24-port 10/100 PoE+ v2 z1 Module <ul style="list-style-type: none">No Transceivers	J9547A
HP 24-port Gig-T v2 z1 Module <ul style="list-style-type: none">No Transceivers	J9550A
HP MSM765 z1 Mobility Controller <ul style="list-style-type: none">No Transceivers	J9370A See Configuration Note:13
HP MSM775 z1 Premium Controller Module <ul style="list-style-type: none">No Transceivers	J9840A See Configuration Note:10
HP Surv Brch Com z1 Mod pwrby Msft Lync <ul style="list-style-type: none">No Transceivers. Double Height Module, takes up 2 Vertical slots*	J9485A See Configuration Note:4, 6, 7, 8, 9, 13
HP Advanced Services v2 z1 Module w/ HDD <ul style="list-style-type: none">No Transceivers	J9857A See Configuration Note:11

Configuration

HP Advanced Services v2 zL Module w/ SSD

- No Transceivers

J9858A
See Configuration
Note:11

HP Adv Svcs zL Mod w/XenServer Platform

- No Transceivers

J9747A
See Configuration
Note:6, 7, 8, 13

HP Adv Svcs zL Mod w/vSphere Platform

- No Transceivers

J9748A
See Configuration
Note:6, 7, 8, 13

Configuration Rules:

Note 1 The following Transceivers install into this Module: (Use #0D1 if switch is CTO) - if applicable

HP X111 100M SFP LC FX Transceiver	J9054C
HP X112 100M SFP LC BX-D Transceiver	J9099B
HP X112 100M SFP LC BX-U Transceiver	J9100B
HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP LC SX Transceiver	J4858C
HP X121 1G SFP LC LX Transceiver	J4859C
HP X122 1G SFP LC BX-D Transceiver	J9142B
HP X122 1G SFP LC BX-U Transceiver	J9143B
HP X121 1G SFP RJ45 T Transceiver	J8177C

Note 2 The following Transceivers install into this Module: (Use #0D1 or #B01 if switch is CTO) - if applicable

HP X132 10G SFP+ LC ER Transceiver	J9153A
HP X132 10G SFP+ LC LR Transceiver	J9151A
HP X132 10G SFP+ LC LRM Transceiver	J9152A
HP X132 10G SFP+ LC SR Transceiver	J9150A
HP X242 10G SFP+ to SFP+ 1m Direct Attach Copper Cable	J9281B
HP X242 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	J9283B
HP X242 10G SFP+ to SFP+ 7m Direct Attach Copper Cable	J9285B
HP X244 10G XFP to SFP+ 1m Direct Attach Copper Cable	J9300A
HP 10G X244 XFP to SFP+ 3m Direct Attach Copper Cable	J9301A
HP 10G X244 XFP to SFP+ 5m Direct Attach Copper Cable	J9302A

Note 3 The following Transceivers install into this Module: (Use #0D1 if switch is CTO) - if applicable

HP X131 10G X2 SC SR Transceiver	J8436A
HP X131 10G X2 SC LR Transceiver	J8437A
HP X131 10G X2 SC ER Transceiver	J8438A
HP X131 10G X2 SC LRM Transceiver	J9144A

Note 4 The following Upgrades install into this Module:

Sangoma 2-port T1/E1/J1 Telephony Card	J9488A
Sangoma 4-port T1/E1/J1 Telephony Card	J9489A
Sangoma 4-port FXO Telephony Card	J9516A
Sangoma 4-port FXS Telephony Card	J9482A
Sangoma 2-p FXO / 2-p FXS Telephony Card	J9518A

Configuration

Sangoma 1-port T1/E1/J1 Telephony Card J9487A

Note 5 The following Transceivers install into this Module: (Use #0D1 or #B01 if switch is CTO) - if applicable

HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP LC SX Transceiver	J4858C
HP X121 1G SFP LC LX Transceiver	J4859C
HP X122 1G SFP LC BX-D Transceiver	J9142B
HP X122 1G SFP LC BX-U Transceiver	J9143B
HP X121 1G SFP RJ45 T Transceiver	J8177C
HP X132 10G SFP+ LC ER Transceiver	J9153A
HP X132 10G SFP+ LC LR Transceiver	J9151A
HP X132 10G SFP+ LC LRM Transceiver	J9152A
HP X132 10G SFP+ LC SR Transceiver	J9150A
HP X242 10G SFP+ to SFP+ 1m Direct Attach Copper Cable	J9281B
HP X242 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	J9283B
HP X242 10G SFP+ to SFP+ 7m Direct Attach Copper Cable	J9285B
HP X244 10G XFP to SFP+ 1m Direct Attach Copper Cable	J9300A
HP 10G X244 XFP to SFP+ 3m Direct Attach Copper Cable	J9301A
HP 10G X244 XFP to SFP+ 5m Direct Attach Copper Cable	J9302A

Note 6 For Switches: J9643A, J9532A, J9540A; If this module is selected, Then Max = 4 Modules of any combination or pairing of the following modules: J9485A, J9747A, J9748A. Double Height Modules occupy 2 vertical slots.

Note 7 If this module is selected, Then show following message:
For better airflow, This module must be located on left side only in the following Switches: J9642A, J9533A, J9539A, J9866A
For better airflow, It is preferred, but not required, that This module be located on left side only in the following Switches: J9643A, J9532A, J9540A.

Note 8 For Switches J9642A, J9533A, J9539A, J9866A; If this module is selected, Then Max = 3 SLOTS on left side of chassis only, of any combination or pairing of the following modules: J9485A, J9747A, J9748A. Double Height Modules occupy 2 vertical slots.

Note 9 This module occupies 2 Vertical Slots.

Note 10 Maximum of this Module per Chassis:
J9642A min=0\max=5 per Chassis
J9533A, J9821A, J9539A, J9866A, J9868A, J9823A, J9824A min=0\max=4 per Chassis
J9643A, J9822A, J9532A, J9540A, J9825A, J9826A min=0\max=6 per Chassis
There are no restrictions on which slots these modules may go in.

Note 11 Maximum of this Module per Chassis:
J9642A, J9821A, J9533A, J9539A, J9866A, J9868A, J9823A, J9824A min=0\max=4 per Chassis
J9643A, J9822A, J9532A, J9540A, J9825A, J9826A min=0\max=6 per Chassis
There are no restrictions on which slots these modules may go in.

Note 12 The following Transceivers install into this Module: (Use #0D1 if switch is CTO) - if applicable
HP X111 100M SFP LC FX Transceiver J9054C

Configuration

HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP LC SX Transceiver	J4858C
HP X121 1G SFP LC LX Transceiver	J4859C
HP X121 1G SFP RJ45 T Transceiver	J8177C

Note 13 This module is NOT Supported on the following Switch Chassis: J9821A, J9868A, J9823A, J9824A, J9822A, J9825A, J9826A

Transceivers

SFP Transceivers

HP X111 100M SFP LC FX Transceiver	J9054C
HP X112 100M SFP LC BX-D Transceiver	J9099B
HP X112 100M SFP LC BX-U Transceiver	J9100B
HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP LC LX Transceiver	J4859C
HP X121 1G SFP LC SX Transceiver	J4858C
HP X122 1G SFP LC BX-D Transceiver	J9142B
HP X122 1G SFP LC BX-U Transceiver	J9143B
HP X121 1G SFP RJ45 T Transceiver	J8177C

SFP+ Transceivers

HP X132 10G SFP+ LC ER Transceiver	J9153A
HP X132 10G SFP+ LC LR Transceiver	J9151A
HP X132 10G SFP+ LC LRM Transceiver	J9152A
HP X132 10G SFP+ LC SR Transceiver	J9150A
HP X242 10G SFP+ SFP+ 1m DAC Cable	J9281B#B01
HP X242 10G SFP+ SFP+ 3m DAC Cable	J9283B#B01
HP X242 10G SFP+ SFP+ 7m DAC Cable	J9285B#B01
HP X244 10G XFP SFP+ 1m DAC Cable	J9300A#B01
HP X244 10G XFP SFP+ 3m DAC Cable	J9301A#B01
HP X244 10G XFP SFP+ 5m DAC Cable	J9302A#B01

X2 Transceivers

HP X131 10G X2 SC ER Transceiver	J8438A
HP X131 10G X2 SC LR Transceiver	J8437A
HP X131 10G X2 SC LRM Transceiver	J9144A
HP X131 10G X2 SC SR Transceiver	J8436A

Internal Power Supplies

J9642ASystem (std 0 // max 2) User Selection (min 1 / max 2)

J9533A, J9866A and J9539A System (std 1 // max 2) User Selection (min 0 / max 1)

J9643A System (std 0 // max 4) User Selection (min 2 / max 4)

Configuration

J9532A and J9540A System (std 2 // max 4) User Selection (min 0 / max 2)

(J9821A, J9868A, J9823A, J9824A) System (std 0 // max 2) User Selection (min 1 / max 2)

(J9822A, J9825A, J9826A) System (std 0 // max 4) User Selection (min 2 / max 4)

HP 1500 W PoE+ zL Power Supply

- includes 1 x c15, 1500w

J9306A
See Configuration
Note:1, 2, 3, 6

PDU Cable NA/MEX/TW/JP

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

J9306A#B2B

PDU Cable ROW

- C15 PDU Jumper Cord (ROW)

J9306A#B2C

High Volt Switch to Wall Power Cord

- NEMA L6-20P Cord (NA/MEX/JP/TW)

J9306A#B2E

HP 875W zL Power Supply

- includes 1 x c15, 875w

J8712A
See Configuration
Note:1, 2, 3, 5, 6

PDU Cable NA/MEX/TW/JP

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

J8712A#B2B

PDU Cable ROW

- C15 PDU Jumper Cord (ROW)

J8712A#B2C

High Volt Switch to Wall Power Cord

- NEMA L6-20P Cord (NA/MEX/JP/TW)

J8712A#B2E

HP 1500 W zL Power Supply

- includes 1 x c19

J8713A
See Configuration
Note:1, 2, 3, 5, 6

PDU Cable NA/MX/TW/JP

- C19 PDU Jumper Cord (NA/MX/TW/JP)

J8713A#B2B

PDU Cable ROW

- C19 PDU Jumper Cord (ROW)

J8713A#B2C

High Volt Switch to Wall Power Cord

- NEMA L6-20P Cord (NA/MEX/JP/TW)

J8713A#B2E

HP 5400R 700W PoE+ zL2 Power Supply

- includes 1 x c13, 700w

J9828A
See Configuration
Note:2, 4, 6, 7

Configuration

PDU Cable NA/MEX/TW/JP	J9828A#B2B
<ul style="list-style-type: none"> C15 PDU Jumper Cord (NA/MEX/TW/JP) 	
PDU Cable ROW	J9828A#B2C
<ul style="list-style-type: none"> C15 PDU Jumper Cord (ROW) 	
High Volt Switch to Wall Power Cord	J9828A#B2E
<ul style="list-style-type: none"> NEMA L6-20P Cord (NA/MEX/JP/TW) 	
HP 5400R 1100W PoE+ zL2 Power Supply	J9829A
<ul style="list-style-type: none"> includes 1 x c15, 1100w 	See Configuration Note:2, 4, 6, 7
PDU Cable NA/MEX/TW/JP	J9829A#B2B
<ul style="list-style-type: none"> C15 PDU Jumper Cord (NA/MEX/TW/JP) 	
PDU Cable ROW	J9829A#B2C
<ul style="list-style-type: none"> C15 PDU Jumper Cord (ROW) 	
High Volt Switch to Wall Power Cord	J9829A#B2E
<ul style="list-style-type: none"> NEMA L6-20P Cord (NA/MEX/JP/TW) 	
HP 5400R 2750W PoE+ zL2 Power Supply	J9830A
<ul style="list-style-type: none"> includes 1 x c19, 2750w 	See Configuration Note:2, 4, 6, 7
PDU Cable NA/MEX/TW/JP	J9830A#B2B
<ul style="list-style-type: none"> C19 PDU Jumper Cord (NA/MEX/TW/JP) 	
PDU Cable ROW	J9830A#B2C
<ul style="list-style-type: none"> C19 PDU Jumper Cord (ROW) 	
High Volt Switch to Wall Power Cord	J9830A#B2E
<ul style="list-style-type: none"> NEMA L6-20P Cord (NA/MEX/JP/TW) 	

Configuration Rules:

- Note 1 Power Supplies cannot be mixed for a switch enclosure
- Note 2 Localization required on orders without #B2B, #B2C or #B2E options.
- Note 3 This power supply is not supported on the J9821A, J9868A, J9823A, J9824A, J9822A, J9825A and J9826A switches.
- Note 4 This power supply is ONLY supported on the J9821A, J9868A, J9823A, J9824A, J9822A, J9825A and J9826A switches.
- Note 5 This power supply is not supported on the J9533A, J9539A, J9532A, J9866A and J9540A switches.

Configuration

Note 6 If #B2E is selected Then replace Localized option with #B2E for power supply and with #B2E for switch. (Offered only in NA, Mexico, Taiwan, and Japan)

Note 7 Power Supplies can be mixed for a switch enclosure

Remarks: If Power Supply is added to switch with power supply, then Switch and Power Supply localization must match.

For J9828A, J9829A, J9830A: Power Supplies can be mixed for a switch enclosure. However, the three different power supplies each require different power cords, and the wall plug that is needed for J9830A is different from the wall plug that is needed for J9828A and J9829A. Moreover, full redundancy and N+1 redundancy are only supported with like power supplies.

Drop down under power supply should offer the following options and results:
 Switch/Router/Power Supply to PDU Power Cord - #B2B in North America, Mexico, Taiwan, and Japan or #B2C ROW. (Watson Default B2B or B2C for Rack Level CTO)
 Switch/Router/Power Supply to Wall Power Cord - Localized Option (Watson Default for BTO and Box Level CTO)
 High Volt Switch/Router/Power Supply to Wall Power Cord - #B2E Option. (Offered only in North America, Mexico, Taiwan, and Japan)

Cables

Multi-Mode Cables

HP .5m Multi-mode OM3 LC/LC FC Cable	AJ833A
HP 1m Multi-mode OM3 LC/LC FC Cable	AJ834A
HP 2 m Multimode OM3 LC/LC FC Cable	AJ835A
HP 5 m Multimode OM3 LC/LC FC Cable	AJ836A
HP 15 m Multimode OM3 LC/LC FC Cable	AJ837A
HP 30 m Multimode OM3 LC/LC FC Cable	AJ838A
HP 50 m Multimode OM3 LC/LC FC Cable	AJ839A
HP Premier Flex LC/LC OM4 2f 1m Cbl	QK732A
HP Premier Flex LC/LC OM4 2f 2m Cbl	QK733A
HP Premier Flex LC/LC OM4 2f 5m Cbl	QK734A
HP Premier Flex LC/LC OM4 2f 15m Cbl	QK735A
HP Premier Flex LC/LC OM4 2f 30m Cbl	QK736A
HP Premier Flex LC/LC OM4 2f 50m Cbl	QK737A

Switch Enclosure Options

Fan Trays

HP 5406R zL2 Switch Fan Tray	J9831A
<ul style="list-style-type: none"> Spare Only 	
HP 5412R zL2 Switch Fan Tray	J9832A
<ul style="list-style-type: none"> Spare Only 	

Mounting Kit



Configuration

HP X450 4U/7U Univ 4-Post Rack Mnt Kit

J9852A
See Configuration
Note:1, 2

Configuration Rules:

Note 1 If this Mounting Kit is ordered with #0D1 then it integrates to the HP Universal Rack. (not the switch)

Note 2 If switches J9821A, J9868A, J9823A, J9824A, J9822A, J9825A and J9826A are installed into a rack, Then this Rack Mounting kit is required.

External Redundant Power Supplies

HP zL Power Supply Shelf

- Height = 3U

J8714A
See Configuration
Note:1

Configuration Rules:

Note 1 This power supply is not supported on the J9821A, J9868A, J9823A, J9824A, J9822A, J9825A and J9826A switches.

Remarks: This shelf allows the addition of 2 extra J9306A - HP 1500 W PoE+ zL Power Supply in order to increase the number of POE+ ports.

Cables included: includes two 2 m PoE (EPS) cables; cables can be used to carry PoE power to the connected switch; no extra cables are needed for a complete solution. Flexible mounting: the power shelf can be mounted forward or rear facing in a rack; in a four-post rack, two power shelves can be mounted front to front, requiring only 3U of rack space.

License

HP MSM760/765 Additional 40 AP License

J9371A

Remarks: The License is an option to the J9370A.

Survivable Branch Communication Upgrades

Sangoma 2-port T1/E1/J1 Telephony Card

J9488A

Sangoma 4-port T1/E1/J1 Telephony Card

J9489A

Sangoma 4-port FXO Telephony Card

J9516A

Sangoma 4-port FXS Telephony Card

J9482A

Sangoma 2-port FXO / 2-port FXS Telephony Card

J9518A

Sangoma 1-port T1/E1/J1 Telephony Card

J9487A

Remarks: The Sangoma Telephony Cards are accessories to the J9485A.

US Federal Government certifications

Configuration

HP zL Chassis FIPS 10K Rack Mounting Kit	J9708A See Configuration Note:1
HP 16mm x 32mm Tmpr-Evidence (20) Labels	J9740A See Configuration Note:1
HP 16mm x 32mm Tmpr-Evidence (120) Label	J9709A See Configuration Note:1
HP 5406 zL FIPS Opacity Shield Kit	J9710A See Configuration Note:1
HP 5412 zL FIPS Opacity Shield Kit	J9711A See Configuration Note:1
HP 5406 zL High Performance Fan Tray	J9721A See Configuration Note:1
HP 5412 zL High Performance Fan Tray	J9722A See Configuration Note:1

Configuration Rules:

Note 1 Do not display in Watson.

Technical Specifications

HP 5406R z12 Switch (J9821A)	Included accessories	1 HP 5400R z12 Management Module (J9827A) 1 HP 5406R z12 Switch Fan Tray (J9831A)	
	I/O ports and slots	6 open module slots Supports a maximum of 48 10GbE ports or 144 autosensing 10/100/1000 ports or 144 SFPs, or a combination	
	Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)	
	Fan tray	includes: 1 x J9831A 1 fan tray slot	
	Physical characteristics	Dimensions	17.5(w) x 17.75(d) x 6.9(h) in (44.45 x 45.09 x 17.53 cm) (4U height)
		Weight	24.5 lb (11.11 kg)
	Memory and processor	Gigabit Module	ARM11 @ 450 MHz; packet buffer size: 18 MB internal
		10G module	ARM11 @ 550 MHz; packet buffer size: 18 MB internal
		Management Module	Freescale P2020 dual core @ 1.2 GHz, 16 MB flash, 1 GB SD Card, 4 GB DDR3 SODIMM
	Mounting	Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included); horizontal surface mounting only	
	Performance	1000 Mb Latency	< 2.9 μ s (FIFO 64-byte packets)
		10 Gbps Latency	< 2.0 μ s (FIFO 64-byte packets)
		Throughput	392.8 Mpps
		Routing/Switching capacity	528 Gb/s
		Switch fabric speed	1015 Gb/s
		Routing table size	10000 entries (IPv4), 5000 entries (IPv6)
		MAC address table size	64000 entries
	Environment	Operating temperature	32°F to 113°F (0°C to 45°C); 0°C to 40°C with J8177C transceiver installed, 0°C to 35°C with FIPS Opacity Shield installed
		Operating relative humidity	15% to 95% @ 113°F (45°C), noncondensing
		Nonoperating/Storage temperature	-40°F to 158°F (-40°C to 70°C)
		Nonoperating/Storage relative humidity	15% to 95% @ 149°F (65°C), noncondensing
		Altitude	up to 10,000 ft (3 km)
	Acoustic	Power: 44 dB, Pressure: 31.7 dB ISO 7779, ISO 9296	
	Electrical characteristics	Frequency	50/60 Hz
		Description	Does not come with power supply. Two power supply slots are available; three different power supplies are available. See power supply products for additional specifications.
		Maximum heat dissipation	2450 BTU/hr (2584 kJ/hr), (max. non-PoE); 3700 BTU/hr (3903 kJ/hr) (max. using PoE)
	AC Voltage	100 - 127 / 200 - 240 VAC	

Technical Specifications

	Notes	Heat dissipation does not include heat dissipated by the PoE-powered devices themselves.
Safety	CSA 22.2 No. 60950; UL 60950; IEC 60950; EN 60950	
Emissions	FCC part 15 Class A; EN 55022/CISPR 22 Class A	
Immunity	EN	EN 55024, CISPR 24
	ESD	IEC 61000-4-2; 4 kV CD, 8 kV AD; HP ENV. 765.002
	Radiated	IEC 61000-4-3; 3 V/m
	EFT/Burst	IEC 61000-4-4; 1.0 kV (power line), 0.5 kV (signal line)
	Surge	IEC 61000-4-5; 1 kV/2 kV AC, 1kV signal, 0.5 kV DC
	Conducted	IEC 61000-4-6; 3 Vrms
	Power frequency magnetic field	IEC 61000-4-8; 1 A/m, 50 or 60 Hz
	Voltage dips and interruptions	IEC 61000-4-11; >95% reduction, 0.5 period; 30% reduction, 25 periods
	Harmonics	EN 61000-3-2, IEC 61000-3-2
	Flicker	EN 61000-3-3, IEC 61000-3-3
Management	IMC - Intelligent Management Center; command-line interface; Web browser; configuration menu; out-of-band management (RJ-45 Ethernet); SNMP Manager; out-of-band management (serial RS-232C or Micro USB)	
Notes	Supported 1G SFP transceivers are revision "B" or later (product number ends with the letter "B" or later; for example, J9142B, J8177C).	
Services	Refer to the HP website at: www.hp.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local HP sales office.	

HP 5412R z12 Switch (J9822A)	Included accessories	1 HP 5400R z12 Management Module (J9827A) 1 HP 5406R z12 Switch Fan Tray (J9831A)
	I/O ports and slots	12 open module slots Supports a maximum of 96 10GbE ports or 288 autosensing 10/100/1000 ports or 288 SFPs, or a combination
	Power supplies	4 power supply slots 2 minimum power supplies required (ordered separately)
	Fan tray	includes: 1 x J9832A 1 fan tray slot
	Physical characteristics	Dimensions 17.5(w) x 17.75(d) x 12.1(h) in (44.45 x 45.09 x 30.73 cm) (7U height) Weight 38.1 lb (17.28 kg)
	Memory and processor	Gigabit Module ARM11 @ 450 MHz; packet buffer size: 18 MB internal 10G module ARM11 @ 550 MHz; packet buffer size: 18 MB internal Management Module Freescale P2020 dual core @ 1.2 GHz, 16 MB flash, 1 GB SD Card, 4 GB DDR3 SODIMM
	Mounting	Mounts in an EIA standard 19-inch telco rack or equipment cabinet

Technical Specifications

		(hardware included); horizontal surface mounting only
Performance	1000 Mb Latency	< 2.9 μ s (FIFO 64-byte packets)
	10 Gbps Latency	< 2.0 μ s (FIFO 64-byte packets)
	Throughput	785.7 Mpps
	Routing/Switching capacity	1.0 Tbps
	Switch fabric speed	2.0 Tbps
	Routing table size	10000 entries (IPv4), 5000 entries (IPv6)
	MAC address table size	64000 entries
Environment	Operating temperature	32°F to 113°F (0°C to 45°C); 0°C to 40°C with J8177C transceiver installed, 0°C to 35°C with FIPS Opacity Shield installed
	Operating relative humidity	15% to 95% @ 113°F (45°C), noncondensing
	Nonoperating/Storage temperature	-40°F to 158°F (-40°C to 70°C)
	Nonoperating/Storage relative humidity	15% to 95% @ 149°F (65°C), noncondensing
	Altitude	up to 10,000 ft (3 km)
	Acoustic	Power: 49 dB, Pressure: 35.7 dB ISO 7779, ISO 9296
	Electrical characteristics	Frequency
Description		Does not come with power supply. Four power supply slots are available; three different power supplies are available. See power supply products for additional specifications.
Maximum heat dissipation		4900 BTU/hr (5169 kJ/hr), (max. non-PoE); 7400 BTU/hr (7,807 kJ/hr) (max. using PoE)
AC Voltage		100 - 127 / 200 - 240 VAC
Notes		Heat dissipation does not include heat dissipated by the PoE-powered devices themselves. When more than four power cords are installed in a 5412R zL2 switch chassis, additional installation requirements are needed. Refer to the HP 5400R zL2 Switches Quick Setup Guide and Safety/Regulatory Information manual for details.
Safety Emissions Immunity		CSA 22.2 No. 60950; UL 60950; IEC 60950; EN 60950 FCC part 15 Class A; EN 55022/CISPR 22 Class A
	EN	EN 55024, CISPR 24
	ESD	IEC 61000-4-2; 4 kV CD, 8 kV AD; HP ENV. 765.002
	Radiated EFT/Burst	IEC 61000-4-3; 3 V/m IEC 61000-4-4; 1.0 kV (power line), 0.5 kV (signal line)
	Surge	IEC 61000-4-5; 1 kV/2 kV AC, 1kV signal, 0.5 kV DC
	Conducted Power frequency	IEC 61000-4-6; 3 Vrms IEC 61000-4-8; 1 A/m, 50 or 60 Hz

Technical Specifications

magnetic field

Voltage dips and interruptions IEC 61000-4-11; >95% reduction, 0.5 period; 30% reduction, 25 periods

Harmonics EN 61000-3-2, IEC 61000-3-2

Flicker EN 61000-3-3, IEC 61000-3-3

Management

IMC - Intelligent Management Center; command-line interface; Web browser; configuration menu; out-of-band management (RJ-45 Ethernet); SNMP Manager; out-of-band management (serial RS-232C or Micro USB)

Notes

Supported 1G SFP transceivers are revision "B" or later (product number ends with the letter "B" or later; for example, J9142B, J8177C).

Services

Refer to the HP website at: www.hp.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local HP sales office.

HP 5406R-44G PoE+/2SFP+ (No PSU) v2 zL2 Switch (J9823A)

Included accessories

1 HP 5400R zL2 Management Module (J9827A)
1 HP 5406R zL2 Switch Fan Tray (J9831A)
1 HP 24-port Gig-T PoE+ v2 zL Module (J9534A)
1 HP 20-port Gig-T PoE+ / 2-port 10GbE SFP+ v2 zL Module (J9536A)

I/O ports and slots

44 RJ-45 autosensing 10/100/1000 PoE+ ports (IEEE 802.3 Type 10BASE-T, IEEE 802.3u Type 100BASE-TX, IEEE 802.3ab Type 1000BASE-T, IEEE 802.3at PoE+); Media Type: Auto MDIX; Duplex: 10BASE-T/100BASE-TX: half or full; 1000BASE-T: full only
2 open 10GbE SFP+ transceiver slots
4 open module slots
Supports a maximum of 34 10GbE ports or 140 autosensing 10/100/1000 ports or 98 SFPs, or a combination

Power supplies

2 power supply slots
1 minimum power supply required (ordered separately)

Fan tray

includes: 1 x J9831A
1 fan tray slot

Physical characteristics

Dimensions 17.5(w) x 17.75(d) x 6.9(h) in (44.45 x 45.09 x 17.53 cm) (4U height)

Weight 28.11 lb (12.75 kg)

Memory and processor

Gigabit Module ARM11 @ 450 MHz; packet buffer size: 18 MB internal

10G module ARM11 @ 550 MHz; packet buffer size: 18 MB internal

Management Module Freescale P2020 dual core @ 1.2 GHz, 16 MB flash, 1 GB SD Card, 4 GB DDR3 SODIMM

Mounting

Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included); horizontal surface mounting only

Performance

1000 Mb Latency < 2.9 is (FIFO 64-byte packets)

10 Gbps Latency < 2.0 is (FIFO 64-byte packets)

Throughput 392.8 Mpps

Routing/Switching capacity 528 Gb/s

Switch fabric speed 1015 Gb/s

Routing table size 10000 entries (IPv4), 5000 entries (IPv6)

MAC address table size 64000 entries

Technical Specifications

Environment	Operating temperature	32°F to 113°F (0°C to 45°C); 0°C to 40°C with J8177C transceiver installed, 0°C to 35°C with FIPS Opacity Shield installed
	Operating relative humidity	15% to 95% @ 113°F (45°C), noncondensing
	Nonoperating/Storage temperature	-40°F to 158°F (-40°C to 70°C)
	Nonoperating/Storage relative humidity	15% to 95% @ 149°F (65°C), noncondensing
	Altitude	up to 10,000 ft (3 km)
	Acoustic	Power: 44 dB, Pressure: 31.7 dB ISO 7779, ISO 9296
	Electrical characteristics	Frequency
Description		Does not come with power supply. Two open power supply slots are available; three different power supplies are available. See power supply products for additional specifications.
Maximum heat dissipation		2450 BTU/hr (2584.75 kJ/hr), (max. non-PoE); 3700 BTU/hr (3903 kJ/hr) (max. using PoE)
AC Voltage		110 - 127 / 200 - 240 VAC
Idle power		215 W
Notes		Idle power is the actual power consumption of the device with no ports connected. Heat dissipation does not include heat dissipated by the PoE-powered devices themselves.
Safety		CSA 22.2 No. 60950; UL 60950; IEC 60950; EN 60950
Emissions	FCC part 15 Class A; EN 55022/CISPR 22 Class A	
Immunity	EN	EN 55024, CISPR 24
	ESD	IEC 61000-4-2; 4 kV CD, 8 kV AD; HP ENV. 765.002
	Radiated	IEC 61000-4-3; 3 V/m
	EFT/Burst	IEC 61000-4-4; 1.0 kV (power line), 0.5 kV (signal line)
	Surge	IEC 61000-4-5; 1 kV/2 kV AC, 1kV signal, 0.5 kV DC
	Conducted	IEC 61000-4-6; 3 Vrms
	Power frequency magnetic field	IEC 61000-4-8; 1 A/m, 50 or 60 Hz
	Voltage dips and interruptions	IEC 61000-4-11; >95% reduction, 0.5 period; 30% reduction, 25 periods
	Harmonics	EN 61000-3-2, IEC 61000-3-2
	Flicker	EN 61000-3-3, IEC 61000-3-3
Management	IMC - Intelligent Management Center; command-line interface; Web browser; configuration menu; out-of-band management (RJ-45 Ethernet); SNMP Manager; out-of-band management (serial RS-232C or Micro USB)	
Notes	Supported 1G SFP transceivers are revision "B" or later (product number ends with the letter "B" or later; for example, J9142B, J8177C).	

Technical Specifications

Services Refer to the HP website at: www.hp.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local HP sales office.

HP 5412R-92G-PoE+/2SFP+ (No PSU) v2 zL2 Switch (J9825A)	Included accessories	1 HP 5400R zL2 Management Module (J9827A) 1 HP 5412R zL2 Switch Fan Tray (J9832A) 3 HP 24-port Gig-T PoE+ v2 zL Module (J9534A) 1 HP 20-port Gig-T PoE+ / 2-port 10GbE SFP+ v2 zL Module (J9536A)	
	I/O ports and slots	92 RJ-45 autosensing 10/100/1000 PoE+ ports (IEEE 802.3 Type 10BASE-T, IEEE 802.3u Type 100BASE-TX, IEEE 802.3ab Type 1000BASE-T, IEEE 802.3at PoE+); Media Type: Auto-MDIX; Duplex: 10BASE-T/100BASE-TX: half or full; 1000BASE-T: full only 2 open 10GbE SFP+ transceiver slots 8 open module slots Supports a maximum of 66 10GbE ports or 284 autosensing 10/100/1000 ports or 194 SFPs, or a combination	
	Power supplies	4 power supply slots 2 minimum power supplies required (ordered separately)	
	Fan tray	includes: 1 x J9832A 1 fan tray slot	
	Physical characteristics	Dimensions	17.5(w) x 17.75(d) x 12.1(h) in (44.45 x 45.09 x 30.73 cm) (7U height)
		Weight	45.19 lb (20.5 kg)
	Memory and processor	Gigabit Module	ARM11 @ 450 MHz; packet buffer size: 18 MB internal
		10G module	ARM11 @ 550 MHz; packet buffer size: 18 MB internal
		Management Module	Freescale P2020 dual core @ 1.2 GHz, 16 MB flash, 1 GB SD Card, 4 GB DDR3 SODIMM
	Mounting	Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included); horizontal surface mounting only	
	Performance	1000 Mb Latency	< 2.9 is (FIFO 64-byte packets)
		10 Gbps Latency	< 2.0 is (FIFO 64-byte packets)
		Throughput	785.7 Mpps
		Routing/Switching capacity	1.0 Tbps
		Switch fabric speed	2.0 Tbps
		Routing table size	10000 entries (IPv4), 5000 entries (IPv6)
		MAC address table size	64000 entries
	Environment	Operating temperature	32°F to 113°F (0°C to 45°C); 0°C to 40°C with J8177C transceiver installed, 0°C to 35°C with FIPS Opacity Shield installed
		Operating relative humidity	15% to 95% @ 113°F (45°C), noncondensing
		Nonoperating/Storage temperature	-40°F to 158°F (-40°C to 70°C)
		Nonoperating/Storage relative humidity	15% to 95% @ 149°F (65°C), noncondensing
		Altitude	up to 10,000 ft (3 km)

Technical Specifications

	Acoustic	Power: 49 dB, Pressure: 35.7 dB ISO 7779, ISO 9296
Electrical characteristics	Frequency	50/60 Hz
	Description	Does not come with power supply. Four power supply slots are available; three different power supplies are available. See power supply products for additional specifications.
	Maximum heat dissipation	4900 BTU/hr (5169 kJ/hr), (max. non-PoE); 7400 BTU/hr (7,807 kJ/hr) (max. using PoE)
	AC Voltage	110 - 127 / 200 - 240 VAC
	Idle power	312 W
	Notes	Idle power is the actual power consumption of the device with no ports connected. Heat dissipation does not include heat dissipated by the PoE-powered devices themselves. When more than four power cords are installed in a 5412R zL2 switch chassis, additional installation requirements are needed. Refer to the HP 5400R zL2 Switches Quick Setup Guide and Safety/Regulatory Information manual for details.
	Safety Emissions Immunity	CSA 22.2 No. 60950; UL 60950; IEC 60950; EN 60950
	FCC part 15 Class A; EN 55022/CISPR 22 Class A	
	EN	EN 55024, CISPR 24
	ESD	IEC 61000-4-2; 4 kV CD, 8 kV AD; HP ENV. 765.002
	Radiated EFT/Burst	IEC 61000-4-3; 3 V/m IEC 61000-4-4; 1.0 kV (power line), 0.5 kV (signal line)
	Surge	IEC 61000-4-5; 1 kV/2 kV AC, 1kV signal, 0.5 kV DC
	Conducted Power frequency magnetic field	IEC 61000-4-6; 3 Vrms IEC 61000-4-8; 1 A/m, 50 or 60 Hz
	Voltage dips and interruptions	IEC 61000-4-11; >95% reduction, 0.5 period; 30% reduction, 25 periods
	Harmonics	EN 61000-3-2, IEC 61000-3-2
	Flicker	EN 61000-3-3, IEC 61000-3-3
Management		IMC - Intelligent Management Center; command-line interface; Web browser; configuration menu; out-of-band management (RJ-45 Ethernet); SNMP Manager; out-of-band management (serial RS-232C or Micro USB)
Notes		Supported 1G SFP transceivers are revision "B" or later (product number ends with the letter "B" or later; for example, J9142B, J8177C).
Services		Refer to the HP website at: www.hp.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local HP sales office.

HP 5406R-44G-PoE+/4SFP (No PSU) v2

Included accessories

- 1 HP 5400R zL2 Management Module (J9827A)
- 1 HP 5406R zL2 Switch Fan Tray (J9831A)

Technical Specifications

z12 Switch (J9824A)

		1 HP 24-port Gig-T PoE+ v2 z1 Module (J9534A) 1 HP 20-port Gig-T PoE+ / 2-port 10GbE SFP+ v2 z1 Module (J9536A)
I/O ports and slots		44 RJ-45 autosensing 10/100/1000 PoE+ ports (IEEE 802.3 Type 10BASE-T, IEEE 802.3u Type 100BASE-TX, IEEE 802.3ab Type 1000BASE-T, IEEE 802.3at PoE+); Media Type: Auto MDIX; Duplex: 10BASE-T/100BASE-TX: half or full; 1000BASE-T: full only 4 open SFP transceiver slots 4 open module slots Supports a maximum of 32 10GbE ports or 140 autosensing 10/100/1000 ports or 100 SFPs, or a combination
Power supplies		2 power supply slots 1 minimum power supply required (ordered separately)
Fan tray		includes: 1 x J9831A 1 fan tray slot
Physical characteristics	Dimensions	17.5(w) x 17.75(d) x 6.9(h) in (44.45 x 45.09 x 17.53 cm) (4U height)
	Weight	26.19 lb (11.88 kg)
Memory and processor	Gigabit Module	ARM11 @ 450 MHz; packet buffer size: 18 MB internal
	10G module	ARM11 @ 550 MHz; packet buffer size: 18 MB internal
	Management Module	Freescall P2020 dual core @ 1.2 GHz, 16 MB flash, 1 GB SD Card, 4 GB DDR3 SODIMM
Mounting		Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included); horizontal surface mounting only
Performance	1000 Mb Latency	< 2.9 is (FIFO 64-byte packets)
	10 Gbps Latency	< 2.0 is (FIFO 64-byte packets)
	Throughput	392.8 Mpps
	Routing/Switching capacity	528 Gb/s
	Switch fabric speed	1015 Gb/s
	Routing table size	10000 entries (IPv4), 5000 entries (IPv6)
	MAC address table size	64000 entries
Environment	Operating temperature	32°F to 113°F (0°C to 45°C); 0°C to 40°C with J8177C transceiver installed, 0°C to 35°C with FIPS Opacity Shield installed
	Operating relative humidity	15% to 95% @ 113°F (45°C), noncondensing
	Nonoperating/Storage temperature	-40°F to 158°F (-40°C to 70°C)
	Nonoperating/Storage relative humidity	15% to 95% @ 149°F (65°C), noncondensing
	Altitude	up to 10,000 ft (3 km)
	Acoustic	Power: 44 dB, Pressure: 31.7 dB ISO 7779, ISO 9296
Electrical characteristics	Frequency	50/60 Hz
	Description	Does not come with power supply. Two open power supply slots are available; three different power supplies are available. See

Technical Specifications

		power supply products for additional specifications.
	Maximum heat dissipation	2450 BTU/hr (2584.75 kJ/hr), (max. non-PoE); 3700 BTU/hr (3903 kJ/hr) (max. using PoE)
	AC Voltage	110 - 127 / 200 - 240 VAC
	Idle power	215 W
	Notes	Idle power is the actual power consumption of the device with no ports connected. Heat dissipation does not include heat dissipated by the PoE-powered devices themselves.
Safety		CSA 22.2 No. 60950; UL 60950; IEC 60950; EN 60950
Emissions		FCC part 15 Class A; EN 55022/CISPR 22 Class A
Immunity	EN	EN 55024, CISPR 24
	ESD	IEC 61000-4-2; 4 kV CD, 8 kV AD; HP ENV. 765.002
	Radiated EFT/Burst	IEC 61000-4-3; 3 V/m IEC 61000-4-4; 1.0 kV (power line), 0.5 kV (signal line)
	Surge	IEC 61000-4-5; 1 kV/2 kV AC, 1kV signal, 0.5 kV DC
	Conducted Power frequency magnetic field	IEC 61000-4-6; 3 Vrms IEC 61000-4-8; 1 A/m, 50 or 60 Hz
	Voltage dips and interruptions	IEC 61000-4-11; >95% reduction, 0.5 period; 30% reduction, 25 periods
	Harmonics	EN 61000-3-2, IEC 61000-3-2
	Flicker	EN 61000-3-3, IEC 61000-3-3
Management		IMC - Intelligent Management Center; command-line interface; Web browser; configuration menu; out-of-band management (RJ-45 Ethernet); SNMP Manager; out-of-band management (serial RS-232C or Micro USB)
Notes		Supported 1G SFP transceivers are revision "B" or later (product number ends with the letter "B" or later; for example, J9142B, J8177C).
Services		Refer to the HP website at: www.hp.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local HP sales office.

HP 5412R-92G-PoE+/4SFP (No PSU) v2 zL2 Switch (J9826A)

Included accessories	1 HP 5400R zL2 Management Module (J9827A) 1 HP 5412R zL2 Switch Fan Tray (J9832A) 3 HP 24-port Gig-T PoE+ v2 zL Module (J9534A) 1 HP 20-port Gig-T PoE+ / 2-port 10GbE SFP+ v2 zL Module (J9536A)
I/O ports and slots	92 RJ-45 autosensing 10/100/1000 PoE+ ports (IEEE 802.3 Type 10BASE-T, IEEE 802.3u Type 100BASE-TX, IEEE 802.3ab Type 1000BASE-T, IEEE 802.3at PoE+); Media Type: Auto-MDIX; Duplex: 10BASE-T/100BASE-TX: half or full; 1000BASE-T: full only 4 open SFP transceiver slots 8 open module slots Supports a maximum of 64 10GbE ports or 284 autosensing 10/100/1000 ports or 196 SFPs, or a combination

Technical Specifications

Power supplies	4 power supply slots 2 minimum power supplies required (ordered separately)	
Fan tray	includes: 1 x J9832A 1 fan tray slot	
Physical characteristics	Dimensions	17.5(w) x 17.75(d) x 12.1(h) in (44.45 x 45.09 x 30.73 cm) (7U height)
	Weight	45.4 lb (20.5 kg)
Memory and processor	Gigabit Module	ARM11 @ 450 MHz; packet buffer size: 18 MB internal
	10G module	ARM11 @ 550 MHz; packet buffer size: 18 MB internal
	Management Module	Freescale P2020 dual core @ 1.2 GHz, 16 MB flash, 1 GB SD Card, 4 GB DDR3 SODIMM
Mounting	Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included); horizontal surface mounting only	
Performance	1000 Mb Latency	< 2.9 is (FIFO 64-byte packets)
	10 Gbps Latency	< 2.0 is (FIFO 64-byte packets)
	Throughput	785.7 Mpps
	Routing/Switching capacity	1.0 Tb/s
	Switch fabric speed	2.0 Tb/s
	Routing table size	10000 entries (IPv4), 5000 entries (IPv6)
	MAC address table size	64000 entries
Environment	Operating temperature	32°F to 113°F (0°C to 45°C); 0°C to 40°C with J8177C transceiver installed, 0°C to 35°C with FIPS Opacity Shield installed
	Operating relative humidity	15% to 95% @ 113°F (45°C), noncondensing
	Nonoperating/Storage temperature	-40°F to 158°F (-40°C to 70°C)
	Nonoperating/Storage relative humidity	15% to 95% @ 149°F (65°C), noncondensing
	Altitude	up to 10,000 ft (3 km)
	Acoustic	Power: 49 dB, Pressure: 35.7 dB ISO 7779, ISO 9296
Electrical characteristics	Frequency	50/60 Hz
	Description	Does not come with power supply. Four power supply slots are available; three different power supplies are available. See power supply products for additional specifications.
	Maximum heat dissipation	4900 BTU/hr (5169 kJ/hr), (max. non-PoE); 7400 BTU/hr (7,807 kJ/hr) (max. using PoE)
	AC Voltage	110 - 127 / 200 - 240 VAC
	Idle power	312 W
	Notes	Idle power is the actual power consumption of the device with no ports connected. Heat dissipation does not include heat dissipated by the PoE-powered devices themselves. When more than four power cords are installed in a

Technical Specifications

5412R zL2 switch chassis, additional installation requirements are needed. Refer to the HP 5400R zL2 Switches Quick Setup Guide and Safety/Regulatory Information manual for details.

Safety	CSA 22.2 No. 60950; UL 60950; IEC 60950; EN 60950
Emissions	FCC part 15 Class A; EN 55022/CISPR 22 Class A
Immunity	<p>EN EN 55024, CISPR 24</p> <p>ESD IEC 61000-4-2; 4 kV CD, 8 kV AD; HP ENV. 765.002</p> <p>Radiated IEC 61000-4-3; 3 V/m</p> <p>EFT/Burst IEC 61000-4-4; 1.0 kV (power line), 0.5 kV (signal line)</p> <p>Surge IEC 61000-4-5; 1 kV/2 kV AC, 1kV signal, 0.5 kV DC</p> <p>Conducted IEC 61000-4-6; 3 Vrms</p> <p>Power frequency magnetic field IEC 61000-4-8; 1 A/m, 50 or 60 Hz</p> <p>Voltage dips and interruptions IEC 61000-4-11; >95% reduction, 0.5 period; 30% reduction, 25 periods</p> <p>Harmonics EN 61000-3-2, IEC 61000-3-2</p> <p>Flicker EN 61000-3-3, IEC 61000-3-3</p>
Management	IMC - Intelligent Management Center; command-line interface; Web browser; configuration menu; out-of-band management (RJ-45 Ethernet); SNMP Manager; out-of-band management (serial RS-232C or Micro USB)
Notes	Supported 1G SFP transceivers are revision "B" or later (product number ends with the letter "B" or later; for example, J9142B, J8177C).
Services	Refer to the HP website at: www.hp.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local HP sales office.

HP 5406R-8XGT/8SFP+ (No PSU) v2 zL2 Switch (J9868A)

Included accessories	1 HP 5400R zL2 Management Module (J9827A) 1 HP 5406R zL2 Switch Fan Tray (J9831A) 1 HP 8-port 10GbE SFP+ v2 zL Module (J9538A) 1 HP 8-port 10GBASE-T v2 zL Module (J9546A)
I/O ports and slots	8 RJ-45 10GbE ports (IEEE 802.3an-2006 Type 10GBASE-T) 8 open 10GbE SFP+ transceiver slots 4 open module slots Supports a maximum of 32 10GbE ports or 96 autosensing 10/100/1000 ports or 96 SFPs, or a combination
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)
Fan tray	includes: 1 x J9831A 1 fan tray slot
Physical characteristics	<p>Dimensions 17.5(w) x 17.75(d) x 6.9(h) in (44.45 x 45.09 x 17.53 cm) (4U height)</p> <p>Weight 28.11 lb (12.75 kg)</p>
Memory and processor	10G module ARM11 @ 550 MHz; packet buffer size: 18 MB internal

Technical Specifications

	Management Module	Freescale P2020 dual core @ 1.2 GHz, 16 MB flash, 1 GB SD Card, 4 GB DDR3 SODIMM
Mounting		Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included); horizontal surface mounting only
Performance	1000 Mb Latency	< 2.9 μ s (FIFO 64-byte packets)
	10 Gbps Latency	< 2.0 μ s (FIFO 64-byte packets)
	Throughput	392.8 Mpps
	Routing/Switching capacity	528 Gb/s
	Switch fabric speed	1015 Gb/s
	Routing table size	10000 entries (IPv4), 5000 entries (IPv6)
	MAC address table size	64000 entries
Environment	Operating temperature	32°F to 113°F (0°C to 45°C); 0°C to 40°C with J8177C transceiver installed, 0°C to 35°C with FIPS Opacity Shield installed
	Operating relative humidity	15% to 95% @ 113°F (45°C), noncondensing
	Nonoperating/Storage temperature	-40°F to 158°F (-40°C to 70°C)
	Nonoperating/Storage relative humidity	15% to 95% @ 149°F (65°C), noncondensing
	Altitude	up to 10,000 ft (3 km)
	Acoustic	Power: 44 dB, Pressure: 31.7 dB ISO 7779, ISO 9296
	Electrical characteristics	Frequency
Description		Does not come with power supply. Two open power supply slots are available; three different power supplies are available. See power supply products for additional specifications.
Maximum heat dissipation		2450 BTU/hr (2584.75 kJ/hr), (max. non-PoE); 3700 BTU/hr (3903 kJ/hr) (max. using PoE)
AC Voltage		110 - 127 / 200 - 240 VAC
Idle power		215 W
Notes		Idle power is the actual power consumption of the device with no ports connected. Heat dissipation does not include heat dissipated by the PoE-powered devices themselves.
CSA 22.2 No. 60950; UL 60950; IEC 60950; EN 60950		
Safety Emissions		FCC part 15 Class A; EN 55022/CISPR 22 Class A
	Immunity	
	EN	EN 55024, CISPR 24
	ESD	IEC 61000-4-2; 4 kV CD, 8 kV AD; HP ENV. 765.002
	Radiated EFT/Burst	IEC 61000-4-3; 3 V/m
	EFT/Burst	IEC 61000-4-4; 1.0 kV (power line), 0.5 kV (signal line)
	Surge	IEC 61000-4-5; 1 kV/2 kV AC, 1kV signal, 0.5 kV DC

Technical Specifications

	Conducted	IEC 61000-4-6; 3 Vrms
	Power frequency magnetic field	IEC 61000-4-8; 1 A/m, 50 or 60 Hz
	Voltage dips and interruptions	IEC 61000-4-11; >95% reduction, 0.5 period; 30% reduction, 25 periods
	Harmonics	EN 61000-3-2, IEC 61000-3-2
	Flicker	EN 61000-3-3, IEC 61000-3-3
Management	IMC - Intelligent Management Center; command-line interface; Web browser; configuration menu; out-of-band management (RJ-45 Ethernet); SNMP Manager; out-of-band management (serial RS-232C or Micro USB)	
Notes	Supported 1G SFP transceivers are revision "B" or later (product number ends with the letter "B" or later; for example, J9142B, J8177C).	
Services	Refer to the HP website at: www.hp.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local HP sales office.	
Standards and protocols (applies to all products in series)	BGP	RFC 1997 BGP Communities Attribute RFC 2918 Route Refresh Capability RFC 4271 A Border Gateway Protocol 4 (BGP-4) RFC 4456 BGP Route Reflection: An Alternative to Full Mesh Internal BGP (IBGP) RFC 5492 Capabilities Advertisement with BGP-4
	Device Management	RFC 1591 DNS (client) HTML and telnet management
	General Protocols	IEEE 802.1ad Q-in-Q IEEE 802.1AX-2008 Link Aggregation IEEE 802.1D MAC Bridges IEEE 802.1p Priority IEEE 802.1Q VLANs IEEE 802.1s Multiple Spanning Trees IEEE 802.1v VLAN classification by Protocol and Port IEEE 802.1w Rapid Reconfiguration of Spanning Tree IEEE 802.3ad Link Aggregation Control Protocol (LACP) IEEE 802.3af Power over Ethernet IEEE 802.3x Flow Control RFC 768 UDP RFC 783 TFTP Protocol (revision 2) RFC 792 ICMP RFC 793 TCP RFC 826 ARP RFC 854 TELNET RFC 868 Time Protocol RFC 951 BOOTP RFC 1058 RIPv1 RFC 1350 TFTP Protocol (revision 2) RFC 1519 CIDR RFC 1542 BOOTP Extensions RFC 2030 Simple Network Time Protocol (SNTP) v4

Technical Specifications

	RFC 2131 DHCP
	RFC 2453 RIPv2
	RFC 2548 (MS-RAS-Vendor only)
	RFC 3046 DHCP Relay Agent Information Option
	RFC 3576 Ext to RADIUS (CoA only)
	RFC 3768 VRRP
	RFC 4675 RADIUS VLAN & Priority
	UDLD (Uni-directional Link Detection)
IP Multicast	RFC 3376 IGMPv3 (host joins only)
	RFC 3973 PIM Dense Mode
	RFC 4601 PIM Sparse Mode
IPv6	RFC 1981 IPv6 Path MTU Discovery
	RFC 2375 IPv6 Multicast Address Assignments
	RFC 2460 IPv6 Specification
	RFC 2464 Transmission of IPv6 over Ethernet Networks
	RFC 2710 Multicast Listener Discovery (MLD) for IPv6
	RFC 2925 Definitions of Managed Objects for Remote Ping, Traceroute, and Lookup Operations (Ping only)
	RFC 3019 MLDv1 MIB
	RFC 3315 DHCPv6 (client and relay)
	RFC 3484 Default Address Selection for IPv6
	RFC 3587 IPv6 Global Unicast Address Format
	RFC 3596 DNS Extension for IPv6
	RFC 3810 MLDv2 for IPv6
	RFC 4022 MIB for TCP
	RFC 4087 IP Tunnel MIB
	RFC 4113 MIB for UDP
	RFC 4213 Basic Transition Mechanisms for IPv6 Hosts and Routers
	RFC 4251 SSHv6 Architecture
	RFC 4252 SSHv6 Authentication
	RFC 4253 SSHv6 Transport Layer
	RFC 4254 SSHv6 Connection
	RFC 4291 IP Version 6 Addressing Architecture
	RFC 4293 MIB for IP
	RFC 4294 IPv6 Node Requirements
	RFC 4419 Key Exchange for SSH
	RFC 4443 ICMPv6
	RFC 4541 IGMP & MLD Snooping Switch
	RFC 4861 IPv6 Neighbor Discovery
	RFC 4862 IPv6 Stateless Address Auto-configuration
	RFC 5095 Deprecation of Type 0 Routing Headers in IPv6
	RFC 5340 OSPFv3 for IPv6
	RFC 5453 Reserved IPv6 Interface Identifiers
	RFC 5519 Multicast Group Membership Discovery
	MIB (MLDv2 only)
	RFC 5722 Handling of Overlapping IPv6 Fragments

Technical Specifications

MIBs	IEEE 802.1ap (MSTP and STP MIB's only) RFC 1213 MIB II RFC 1493 Bridge MIB RFC 1724 RIPv2 MIB RFC 1850 OSPFv2 MIB RFC 2021 RMONv2 MIB RFC 2096 IP Forwarding Table MIB RFC 2613 SMON MIB RFC 2618 RADIUS Client MIB RFC 2620 RADIUS Accounting MIB RFC 2665 Ethernet-Like-MIB RFC 2668 802.3 MAU MIB RFC 2674 802.1p and IEEE 802.1Q Bridge MIB RFC 2737 Entity MIB (Version 2) RFC 2787 VRRP MIB RFC 2863 The Interfaces Group MIB RFC 2925 Ping MIB RFC 2933 IGMP MIB
Network Management	IEEE 802.1AB Link Layer Discovery Protocol (LLDP) RFC 2819 Four groups of RMON: 1 (statistics), 2 (history), 3 (alarm) and 9 (events) RFC 3176 sFlow ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED) SNMPv1/v2c/v3 XRMON
OSPF	RFC 2328 OSPFv2 RFC 3101 OSPF NSSA RFC 5340 OSPFv3 for IPv6
QoS/CoS	RFC 2474 DiffServ Precedence, including 8 queues/port RFC 2597 DiffServ Assured Forwarding (AF) RFC 2598 DiffServ Expedited Forwarding (EF)
Security	IEEE 802.1X Port Based Network Access Control RFC 1492 TACACS+ RFC 2865 RADIUS (client only) RFC 2866 RADIUS Accounting RFC 3579 RADIUS Support For Extensible Authentication Protocol (EAP) Secure Sockets Layer (SSL) SSHv2 Secure Shell

Accessories

HP 5400R z12 Switch Series accessories

Modules

HP 8-port 10GBASE-T v2 z1 Module	J9546A
HP 8-port 10GbE SFP+ v2 z1 Module	J9538A
HP 20p GT PoE+ / 2p SFP+ v2 z1 Module	J9536A
HP 20-port GT PoE+/4-port SFP v2 z1 Mod	J9535A
HP 24-port SFP v2 z1 Module	J9537A
HP 12-port Gig-T PoE+ / 12-port SFP v2 z1 Module	J9637A
HP 24-port Gig-T PoE+ v2 z1 Module	J9534A
HP 24-port 10/100 PoE+ v2 z1 Module	J9547A
HP 24-port Gig-T v2 z1 Module	J9550A
HP 20-port Gig-T / 4-port SFP v2 z1 Mod	J9549A
HP 20-port Gig-T / 2-port SFP+ v2 z1 Mod	J9548A
HP Advanced Services v2 z1 Module with HDD	J9857A
HP Advanced Services v2 z1 Module with SSD	J9858A
NEW HP 5400R z12 Management Module	J9827A

Transceivers

HP X131 10G X2 SC ER Transceiver	J8438A
HP X131 10G X2 SC SR Transceiver	J8436A
HP X131 10G X2 CX4 Transceiver	J8440C
HP X111 100M SFP LC FX Transceiver	J9054C
HP X131 10G X2 SC LR Transceiver	J8437A
HP X131 10G X2 SC LRM Transceiver	J9144A
HP X112 100M SFP LC BX-D Transceiver	J9099B
HP X112 100M SFP LC BX-U Transceiver	J9100B
HP X132 10G SFP+ LC SR Transceiver	J9150A
HP X132 10G SFP+ LC LR Transceiver	J9151A
HP X132 10G SFP+ LC LRM Transceiver	J9152A
HP X121 1G SFP LC LH Transceiver	J4860C
HP X121 1G SFP LC SX Transceiver	J4858C
HP X121 1G SFP LC LX Transceiver	J4859C
HP X121 1G SFP RJ45 T Transceiver	J8177C
HP X122 1G SFP LC BX-D Transceiver	J9142B
HP X122 1G SFP LC BX-U Transceiver	J9143B
HP X132 10G SFP+ LC ER Transceiver	J9153A

Cables

HP X242 10G SFP+ to SFP+ 1m Direct Attach Copper Cable	J9281B
HP X242 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	J9283B
HP X242 10G SFP+ to SFP+ 7m Direct Attach Copper Cable	J9285B
HP X244 10G XFP to SFP+ 1m Direct Attach Copper Cable	J9300A
HP 10G X244 XFP to SFP+ 3m Direct Attach Copper Cable	J9301A
HP 10G X244 XFP to SFP+ 5m Direct Attach Copper Cable	J9302A
HP LC to LC Multi-mode OM3 2-Fiber 0.5m 1-Pack Fiber Optic Cable	AJ833A
HP LC to LC Multi-mode OM3 2-Fiber 1.0m 1-Pack Fiber Optic Cable	AJ834A

Accessories

HP LC to LC Multi-mode OM3 2-Fiber 2.0m 1-Pack Fiber Optic Cable	AJ835A
HP LC to LC Multi-mode OM3 2-Fiber 5.0m 1-Pack Fiber Optic Cable	AJ836A
HP LC to LC Multi-mode OM3 2-Fiber 15.0m 1-Pack Fiber Optic Cable	AJ837A
HP LC to LC Multi-mode OM3 2-Fiber 30.0m 1-Pack Fiber Optic Cable	AJ838A
HP LC to LC Multi-mode OM3 2-Fiber 50.0m 1-Pack Fiber Optic Cable	AJ839A
HP Premier Flex LC/LC Multi-mode OM4 2 fiber 1m Cable	QK732A
HP Premier Flex LC/LC Multi-mode OM4 2 fiber 2m Cable	QK733A
HP Premier Flex LC/LC Multi-mode OM4 2 fiber 5m Cable	QK734A
HP Premier Flex LC/LC Multi-mode OM4 2 fiber 15m Cable	QK735A
HP Premier Flex LC/LC Multi-mode OM4 2 fiber 30m Cable	QK736A
HP Premier Flex LC/LC Multi-mode OM4 2 fiber 50m Cable	QK737A
HP X242 10G SFP+ to SFP+ 10m Direct Attach Copper Cable	J9286B
HP X242 10G SFP+ to SFP+ 15m Direct Attach Copper Cable	J9287B
Power Supply	
NEW HP 5400R 700W PoE+ zL2 Power Supply	J9828A
NEW HP 5400R 1100W PoE+ zL2 Power Supply	J9829A
NEW HP 5400R 2750W PoE+ zL2 Power Supply	J9830A
Mounting Kit	
NEW HP X450 4U/7U Universal 4-Post Rack Mounting Kit	J9852A
License	
HP MSM Additional 40 Access Point License	J9371A
HP MSM Additional 40 Access Point E-LTU	J9371AAE
WLAN	
HP MSM775 zL Premium Controller Module	J9840A
HP 5406R zL2 Switch (J9821A)	
NEW HP 5406R zL2 Switch Fan Tray	J9831A
HP 5412R zL2 Switch (J9822A)	
NEW HP 5412R zL2 Switch Fan Tray	J9832A
HP 5406R-44G-PoE+/2SFP+ (No PSU) v2 zL2 Switch (J9823A)	
NEW HP 5406R zL2 Switch Fan Tray	J9831A
HP 5412R-92G-PoE+/2SFP+ (No PSU) v2 zL2 Switch (J9825A)	
NEW HP 5412R zL2 Switch Fan Tray	J9832A
HP 5406R-44G-PoE+/4SFP (No PSU) v2 zL2 Switch (J9824A)	
NEW HP 5406R zL2 Switch Fan Tray	J9831A
HP 5412R-92G-PoE+/4SFP (No PSU) v2 zL2 Switch (J9826A)	
NEW HP 5412R zL2 Switch Fan Tray	J9832A
HP 5406R-8XGT/8SFP+ (No PSU) v2 zL2 Switch (J9868A)	
NEW HP 5406R zL2 Switch Fan Tray	J9831A

Summary of Changes

Date	Version History	Action	Description of Change:
05-September-2014	From Version 3 to 4	Changed	Updated Configuration Menu
14-July-2014	From Version 2 to 3	Changed	Updated Overview section and Technical Specifications
17-June-2014	From Version 1 to 2	Changed	Updated I/O ports and slots in several models and also added the WLAN section to Accessories.

Summary of Changes

To learn more, visit: hp.com/networking

© Copyright 2014 Hewlett-Packard Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.